



(19)

Europäisches Patentamt
 European Patent Office
 Office européen des brevets



(11)

EP 1 125 285 B1

(12)

EUROPEAN PATENT SPECIFICATION

(45) Date of publication and mention
of the grant of the patent:

30.07.2003 Bulletin 2003/31

(51) Int Cl.7: G10L 21/02

(21) Application number: 99952200.6

(86) International application number:
PCT/CA99/01009

(22) Date of filing: 27.10.1999

(87) International publication number:
WO 00/025303 (04.05.2000 Gazette 2000/18)

(54) PERIODICITY ENHANCEMENT IN DECODING WIDEBAND SIGNALS

VERBESSERUNG DER PERIODIZITÄT EINES BREITBANDSIGNALS

AMELIORATION DE LA PERIODICITE DANS LE DECODAGE DE SIGNAUX A LARGE BANDE

(84) Designated Contracting States:

AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE

- SALAMI, Redwan
Sherbrooke, Quebec J1J 4L3 (CA)
- LEFEBRE, Roch
Canton de Magog, Quebec J1K 5R9 (CA)

(30) Priority: 27.10.1998 CA 2252170

(74) Representative: Audier, Philippe André
Brevatome,
3, rue du Docteur Lancereaux
75008 Paris (FR)(43) Date of publication of application:
22.08.2001 Bulletin 2001/34

(73) Proprietor: Voiceage Corporation

Ville Mont-Royal, Quebec H3R 2H6 (CA)

(56) References cited:
EP-A- 0 658 874 EP-A- 0 788 091

(72) Inventors:

- BESSETTE, Bruno
Rock Forest, Quebec J1N 1L2 (CA)

Note: Within nine months from the publication of the mention of the grant of the European patent, any person may give notice to the European Patent Office of opposition to the European patent granted. Notice of opposition shall be filed in a written reasoned statement. It shall not be deemed to have been filed until the opposition fee has been paid. (Art. 99(1) European Patent Convention).

Description

BACKGROUND OF THE INVENTION

5 1. Field of the invention:

[0001] The present invention relates to a method and device for enhancing periodicity of the excitation of a signal synthesis filter in view of producing a synthesized wideband signal.

10 2. Brief description of the prior art:

[0002] The demand for efficient digital wideband speech/audio encoding techniques with a good subjective quality/bit rate trade-off is increasing for numerous applications such as audio/video teleconferencing, multimedia, and wireless applications, as well as Internet and packet network applications. Until recently, telephone bandwidths filtered in the range 200-3400 Hz were mainly used in speech coding applications. However, there is an increasing demand for wideband speech applications in order to increase the intelligibility and naturalness of the speech signals. A bandwidth in the range 50-7000 Hz was found sufficient for delivering a face-to-face speech quality. For audio signals, this range gives an acceptable audio quality, but still lower than the CD quality which operates on the range 20-20000 Hz.

[0003] A speech encoder converts a speech signal into a digital bitstream which is transmitted over a communication channel (or stored in a storage medium). The speech signal is digitized (sampled and quantized with usually 16-bits per sample) and the speech encoder has the role of representing these digital samples with a smaller number of bits while maintaining a good subjective speech quality. The speech decoder or synthesizer operates on the transmitted or stored bit stream and converts it back to a sound signal.

[0004] One of the best prior art techniques capable of achieving a good quality/bit rate trade-off is the so-called Code Excited Linear Prediction (CELP) technique. According to this technique, the sampled speech signal is processed in successive blocks of L samples usually called *frames* where L is some predetermined number (corresponding to 10-30 ms of speech). In CELP, a linear prediction (LP) synthesis filter is computed and transmitted every frame. The L -sample frame is then divided into smaller blocks called *subframes* of size N samples, where $L=kN$ and k is the number of subframes in a frame (N usually corresponds to 4-10 ms of speech). An excitation signal is determined in each subframe, which usually consists of two components: one from the past excitation (also called pitch contribution or adaptive codebook or pitch codebook) and the other from an innovative codebook (also called fixed codebook). This excitation signal is transmitted and used at the decoder as the input of the LP synthesis filter in order to obtain the synthesized speech.

[0005] An innovative codebook in the CELP context, is an indexed set of N -sample-long sequences which will be referred to as N -dimensional codevectors. Each codebook sequence is indexed by an integer k ranging from 1 to M where M represents the size of the codebook often expressed as a number of bits b , where $M=2^b$.

[0006] To synthesize speech according to the CELP technique, each block of N samples is synthesized by filtering an appropriate codevector from a codebook through time varying filters modeling the spectral characteristics of the speech signal. At the encoder end, the synthesis output is computed for all, or a subset, of the codevectors from the codebook (codebook search). The retained codevector is the one producing the synthesis output closest to the original speech signal according to a perceptually weighted distortion measure. This perceptual weighting is performed using a so-called perceptual weighting filter, which is usually derived from the LP synthesis filter.

[0007] A known CELP-based coder is described in the document EP-A-0788091.

[0008] The CELP model has been very successful in encoding telephone band sound signals, and several CELP-based standards exist in a wide range of applications, especially in digital cellular applications. In the telephone band, the sound signal is band-limited to 200-3400 Hz and sampled at 8000 samples/sec. In wideband speech/audio applications, the sound signal is band-limited to 50-7000 Hz and sampled at 16000 samples/sec.

[0009] Some difficulties arise when applying the telephone-band optimized CELP model to wideband signals, and additional features need to be added to the model in order to obtain high quality wideband signals.

[0010] Enhancing the periodicity of the excitation signal improves the quality in case of voiced segments. This was done in the past by filtering the innovative codevector from the fixed codebook through a filter having a transfer function of the form $1/(1-\epsilon bz^T)$ where ϵ is a factor below 0.5 which controls the amount of introduced periodicity. This approach is less efficient in case of wideband signals since it introduces the periodicity over the entire spectrum.

55 OBJECT OF THE INVENTION

[0011] An object of the present invention is to propose a new alternative approach by which periodicity enhancement is achieved through filtering the innovative codevector by an innovation filter which reduces the low-frequency contents

of the innovative codevector, whereby the innovative contribution is reduced mainly at low frequencies to enhance the periodicity of the excitation signal at low frequencies more than high frequencies.

SUMMARY OF THE INVENTION

[0012] More specifically, in accordance with the present invention, there is provided a method for enhancing periodicity of an excitation signal produced in relation to a pitch codevector and an innovative codevector for supplying a signal synthesis filter in view synthesizing a wideband signal. In this periodicity enhancing method, a periodicity factor related to the wideband signal is calculated. Then, the innovative codevector is filtered in relation to the periodicity factor to thereby reduce energy of a low frequency portion of the innovative codevector and enhance periodicity of a low frequency portion of the excitation signal.

[0013] The device of the invention, for enhancing periodicity of an excitation signal produced in relation to adaptive and innovative codevectors for supplying a signal synthesis filter in view of synthesizing a wideband signal, comprises:

- 15** a) a factor generator for calculating a periodicity factor related to said wideband signal; and
 b) an innovative filter for filtering the innovative codevector in relation to the periodicity factor to thereby reduce energy of a low frequency portion of the innovative codevector and enhance periodicity of a low frequency portion of the excitation signal.

20 **[0014]** According to a first preferred embodiment:

- the innovative codevector is filtered with a transfer function of the form:

$$25 \quad F(z) = -\alpha z + 1 - \alpha z^{-1}$$

where α is the periodicity factor derived from a level of periodicity of the excitation signal; and

- 30** - the periodicity factor α is calculated using the relation:

$$\alpha = qR_p$$

35 bounded by $\alpha < q$

where q is an enhancement factor set for example to 0.25, and where

$$40 \quad R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

45

where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal, or the relation:

$$50 \quad \alpha = 0.125(1 + r_v),$$

where

$$55 \quad r_v = (E_v - E_c) / (E_v + E_c)$$

where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

[0015] According to a second preferred embodiment:

- the innovative codevector is filtered with a transfer function of the form:

5

$$F(z) = 1 - \sigma z^{-1}$$

where σ is a periodicity factor derived from a level of periodicity of the excitation signal; and

10

- the periodicity factor σ is calculated using the relation:

$$\sigma = 2qR_p$$

15

bounded by $\sigma < 2q$

where q is an enhancement factor set for example to 0.25, and where

20

$$R_p = \frac{b^2 v_T^t v_T}{u^t u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

25

where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal, or the relation:

30

$$\sigma = 0.25 (1 + r_v),$$

where

35

$$r_v = (E_v - E_c) / (E_v + E_c)$$

where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

[0016] The present invention further relates to a decoder for producing a synthesized wideband signal, comprising:

40

- a) a signal fragmenting device for receiving an encoded wideband signal and extracting from this encoded wideband signal at least pitch codebook parameters, innovative codebook parameters, and synthesis filter coefficients;
- b) a pitch codebook responsive to the pitch codebook parameters for producing a pitch codevector;
- c) an innovative codebook responsive to innovative codebook parameters for producing an innovative codevector;
- d) a periodicity enhancing device as described above, comprising the factor generator for calculating a periodicity factor related to the wideband signal; and the innovation filter for filtering the innovative codevector in relation to the periodicity factor;
- e) a combiner circuit for combining the pitch codevector and the innovative codevector filtered by the innovation filter to thereby produce a periodicity-enhanced excitation signal; and
- f) a signal synthesis filter for filtering that periodicity-enhanced excitation signal in relation to the synthesis filter coefficients to thereby produce the synthesized wideband signal.

45

50

[0017] According to the present invention, in a decoder for producing a synthesized wideband signal, comprising: a signal fragmenting device for receiving an encoded wideband signal and extracting from this encoded wideband signal at least pitch codebook parameters, innovative codebook parameters, and synthesis filter coefficients; an pitch codebook responsive to the pitch codebook parameters for producing a pitch codevector; an innovative codebook responsive to innovative codebook parameters for producing an innovative codevector; a combiner circuit for combining the pitch

codevector and the innovative codevector to thereby produce an excitation signal; and a signal synthesis filter for filtering that excitation signal in relation to the synthesis filter coefficients to thereby produce the synthesized wideband signal;

the improvement therein comprising a periodicity enhancing device as described above, comprising the factor generator for calculating a periodicity factor related to the wideband signal; and the innovation filter for filtering the innovative codevector in relation to the periodicity factor before supplying this innovative codevector to the combiner circuit.

[0018] The present invention still further relates to a cellular communication system, a cellular mobile transmitter/receiver unit, a cellular network element, and a bidirectional wireless communication sub-system comprising the above described decoder.

[0019] The objects, advantages and other features of the present invention will become more apparent upon reading of the following non restrictive description of a preferred embodiment thereof, given by way of example only with reference to the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

[0020] In the appended drawings:

Figure 1 is a schematic block diagram of a preferred embodiment of wideband encoding device;

Figure 2 is a schematic block diagram of a preferred embodiment of wideband decoding device;

Figure 3 is a schematic block diagram of a preferred embodiment of pitch analysis device; and

Figure 4 is a simplified, schematic block diagram of a cellular communication system in which the wideband encoding device of Figure 1 and the wideband decoding device of Figure 2 can be used.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

[0021] As well known to those of ordinary skill in the art, a cellular communication system such as 401 (see Figure 4) provides a telecommunication service over a large geographic area by dividing that large geographic area into a number C of smaller cells. The C smaller cells are serviced by respective cellular base stations 402₁, 402₂ ... 402_C to provide each cell with radio signalling, audio and data channels.

[0022] Radio signalling channels are used to page mobile radiotelephones (mobile transmitter/receiver units) such as 403 within the limits of the coverage area (cell) of the cellular base station 402, and to place calls to other radiotelephones 403 located either inside or outside the base station's cell or to another network such as the Public Switched Telephone Network (PSTN) 404.

[0023] Once a radiotelephone 403 has successfully placed or received a call, an audio or data channel is established between this radiotelephone 403 and the cellular base station 402 corresponding to the cell in which the radiotelephone 403 is situated, and communication between the base station 402 and radiotelephone 403 is conducted over that audio or data channel. The radiotelephone 403 may also receive control or timing information over a signalling channel while a call is in progress.

[0024] If a radiotelephone 403 leaves a cell and enters another adjacent cell while a call is in progress, the radiotelephone 403 hands over the call to an available audio or data channel of the new cell base station 402. If a radiotelephone 403 leaves a cell and enters another adjacent cell while no call is in progress, the radiotelephone 403 sends a control message over the signalling channel to log into the base station 402 of the new cell. In this manner mobile communication over a wide geographical area is possible.

[0025] The cellular communication system 401 further comprises a control terminal 405 to control communication between the cellular base stations 402 and the PSTN 404, for example during a communication between a radiotelephone 403 and the PSTN 404, or between a radiotelephone 403 located in a first cell and a radiotelephone 403 situated in a second cell.

[0026] Of course, a bidirectional wireless radio communication subsystem is required to establish an audio or data channel between a base station 402 of one cell and a radiotelephone 403 located in that cell. As illustrated in very simplified form in Figure 4, such a bidirectional wireless radio communication subsystem typically comprises in the radiotelephone 403:

- a transmitter 406 including:
 - an encoder 407 for encoding the voice signal; and

- a transmission circuit 408 for transmitting the encoded voice signal from the encoder 407 through an antenna such as 409; and
- a receiver 410 including:

- 5
- a receiving circuit 411 for receiving a transmitted encoded voice signal usually through the same antenna 409; and
 - a decoder 412 for decoding the received encoded voice signal from the receiving circuit 411.

10 [0027] The radiotelephone further comprises other conventional radiotelephone circuits 413 to which the encoder 407 and decoder 412 are connected and for processing signals therefrom, which circuits 413 are well known to those of ordinary skill in the art and, accordingly, will not be further described in the present specification.

[0028] Also, such a bidirectional wireless radio communication subsystem typically comprises in the base station 402:

- 15
- a transmitter 414 including:
 - an encoder 415 for encoding the voice signal; and
 - a transmission circuit 416 for transmitting the encoded voice signal from the encoder 415 through an antenna such as 417; and

- 20
- a receiver 418 including:
 - a receiving circuit 419 for receiving a transmitted encoded voice signal through the same antenna 417 or through another antenna (not shown); and
 - a decoder 420 for decoding the received encoded voice signal from the receiving circuit 419.

[0029] The base station 402 further comprises, typically, a base station controller 421, along with its associated database 422, for controlling communication between the control terminal 405 and the transmitter 414 and receiver 418.

30 [0030] As well known to those of ordinary skill in the art, voice encoding is required in order to reduce the bandwidth necessary to transmit sound signal, for example voice signal such as speech, across the bidirectional wireless radio communication subsystem, i.e., between a radiotelephone 403 and a base station 402.

35 [0031] LP voice encoders (such as 415 and 407) typically operating at 13 kbits/second and below such as Code-Excited Linear Prediction (CELP) encoders typically use a LP synthesis filter to model the short-term spectral envelope of the voice signal. The LP information is transmitted, typically, every 10 or 20 ms to the decoder (such 420 and 412) and is extracted at the decoder end.

40 [0032] The novel techniques disclosed in the present specification may apply to different LP-based coding systems. However, a CELP-type coding system is used in the preferred embodiment for the purpose of presenting a non-limitative illustration of these techniques. In the same manner, such techniques can be used with sound signals other than voice and speech as well with other types of wideband signals.

45 [0033] Figure 1 shows a general block diagram of a CELP-type speech encoding device 100 modified to better accommodate wideband signals.

[0034] The sampled input speech signal 114 is divided into successive L -sample blocks called "frames". In each frame, different parameters representing the speech signal in the frame are computed, encoded, and transmitted. LP parameters representing the LP synthesis filter are usually computed once every frame. The frame is further divided into smaller blocks of N samples (blocks of length N), in which excitation parameters (pitch and innovation) are determined. In the CELP literature, these blocks of length N are called "subframes" and the N -sample signals in the subframes are referred to as N -dimensional vectors. In this preferred embodiment, the length N corresponds to 5 ms while the length L corresponds to 20 ms, which means that a frame contains four subframes ($N=80$ at the sampling rate of 16 kHz and 64 after down-sampling to 12.8 kHz). Various N -dimensional vectors occur in the encoding procedure. A list of the vectors which appear in Figures 1 and 2 as well as a list of transmitted parameters are given herein below:

List of the main N -dimensional vectors

[0035]

- 55
- s Wideband signal input speech vector (after down-sampling, preprocessing, and preemphasis);
 - s_w Weighted speech vector;
 - s_0 Zero-input response of weighted synthesis filter;

s_p	Down-sampled pre-processed signal; Oversampled synthesized speech signal;
s'	Synthesis signal before deemphasis;
s_d	Deemphasized synthesis signal;
5 s_h	Synthesis signal after deemphasis and postprocessing;
x	Target vector for pitch search;
x'	Target vector for innovation search;
h	Weighted synthesis filter impulse response;
v_T	Adaptive (pitch) codebook vector at delay T ;
10 y_T	Filtered pitch codebook vector (v_T convolved with h);
c_k	Innovative codevector at index k (k -th entry from the innovation codebook);
c_f	Enhanced scaled innovation codevector;
u	Excitation signal (scaled innovation and pitch codevectors);
u'	Enhanced excitation;
15 z	Band-pass noise sequence;
w'	White noise sequence; and
w	Scaled noise sequence.

List of transmitted parameters

20 STP	Short term prediction parameters (defining $A(z)$);
T	Pitch lag (or pitch codebook index);
25 b	Pitch gain (or pitch codebook gain);
j	Index of the low-pass filter used on the pitch codevector;
k	Codevector index (innovation codebook entry); and
g	Innovation codebook gain.

30 [0037] In this preferred embodiment, the STP parameters are transmitted once per frame and the rest of the parameters are transmitted four times per frame (every subframe).

ENCODER SIDE

35 [0038] The sampled speech signal is encoded on a block by block basis by the encoding device 100 of Figure 1 which is broken down into eleven modules numbered from 101 to 111.

[0039] The input speech is processed into the above mentioned L-sample blocks called frames.

[0040] Referring to Figure 1, the sampled input speech signal 114 is down-sampled in a down-sampling module 101. For example, the signal is down-sampled from 16 kHz down to 12.8 kHz, using techniques well known to those of ordinary skill in the art. Down-sampling down to another frequency can of course be envisaged. Down-sampling increases the coding efficiency, since a smaller frequency bandwidth is encoded. This also reduces the algorithmic complexity since the number of samples in a frame is decreased. The use of down-sampling becomes significant when the bit rate is reduced below 16 kbit/s, although down-sampling is not essential above 16 kbit/s.

[0041] After down-sampling, the 320-sample frame of 20 ms is reduced to 256-sample frame (down-sampling ratio of 4/5).

[0042] The input frame is then supplied to the optional pre-processing block 102. Pre-processing block 102 may consist of a high-pass filter with a 50 Hz cut-off frequency. High-pass filter 102 removes the unwanted sound components below 50 Hz.

[0043] The down-sampled pre-processed signal is denoted by $S_p(n)$, $n=0, 1, 2, \dots, L-1$, where L is the length of the frame (256 at a sampling frequency of 12.8 kHz). In a preferred embodiment of the preemphasis filter 103, the signal $S_p(n)$ is preemphasized using a filter having the following transfer function:

$$P(z) = 1 - \mu z^{-1}$$

55 where μ is a preemphasis factor with a value located between 0 and 1 (a typical value is $\mu = 0.7$). A higher-order filter could also be used. It should be pointed out that high-pass filter 102 and preemphasis filter 103 can be interchanged to obtain more efficient fixed-point implementations.

[0044] The function of the preemphasis filter 103 is to enhance the high frequency contents of the input signal. It also reduces the dynamic range of the input speech signal, which renders it more suitable for fixed-point implementation. Without preemphasis, LP analysis in fixed-point using single-precision arithmetic is difficult to implement.

[0045] Preemphasis also plays an important role in achieving a proper overall perceptual weighting of the quantization error, which contributes to improved sound quality. This will be explained in more detail herein below.

[0046] The output of the preemphasis filter 103 is denoted $s(n)$. This signal is used for performing LP analysis in calculator module 104. LP analysis is a technique well known to those of ordinary skill in the art. In this preferred embodiment, the autocorrelation approach is used. In the autocorrelation approach, the signal $s(n)$ is first windowed using a Hamming window (having usually a length of the order of 30-40 ms). The autocorrelations are computed from the windowed signal, and Levinson-Durbin recursion is used to compute LP filter coefficients, a_i , where $i=1,\dots,p$, and where p is the LP order, which is typically 16 in wideband coding. The parameters a_i are the coefficients of the transfer function of the LP filter, which is given by the following relation:

$$A(z) = 1 + \sum_{i=1}^p a_i z^{-i}$$

[0047] LP analysis is performed in calculator module 104, which also performs the quantization and interpolation of the LP filter coefficients. The LP filter coefficients are first transformed into another equivalent domain more suitable for quantization and interpolation purposes. The line spectral pair (LSP) and immittance spectral pair (ISP) domains are two domains in which quantization and interpolation can be efficiently performed. The 16 LP filter coefficients, a_i , can be quantized in the order of 30 to 50 bits using split or multi-stage quantization, or a combination thereof. The purpose of the interpolation is to enable updating the LP filter coefficients every subframe while transmitting them once every frame, which improves the encoder performance without increasing the bit rate. Quantization and interpolation of the LP filter coefficients is believed to be otherwise well known to those of ordinary skill in the art and, accordingly, will not be further described in the present specification.

[0048] The following paragraphs will describe the rest of the coding operations performed on a subframe basis. In the following description, the filter $A(z)$ denotes the unquantized interpolated LP filter of the subframe, and the filter $\hat{A}(z)$ denotes the quantized interpolated LP filter of the subframe.

Perceptual Weighting:

[0049] In analysis-by-synthesis encoders, the optimum pitch and innovation parameters are searched by minimizing the mean squared error between the input speech and synthesized speech in a perceptually weighted domain. This is equivalent to minimizing the error between the weighted input speech and weighted synthesis speech.

[0050] The weighted signal $s_w(n)$ is computed in a perceptual weighting filter 105. Traditionally, the weighted signal $s_w(n)$ is computed by a weighting filter having a transfer function $W(z)$ in the form:

$$W(z) = A(z/\gamma_1) / A(z/\gamma_2)$$

where

$$0 < \gamma_2 < \gamma_1 \leq 1$$

[0051] As well known to those of ordinary skill in the art, in prior art analysis-by-synthesis (AbS) encoders, analysis shows that the quantization error is weighted by a transfer function $W^{-1}(z)$, which is the inverse of the transfer function of the perceptual weighting filter 105. This result is well described by B.S. Atal and M.R. Schroeder in "Predictive coding of speech and subjective error criteria", IEEE Transaction ASSP, vol. 27, no. 3, pp. 247-254, June 1979. Transfer function $W^{-1}(z)$ exhibits some of the formant structure of the input speech signal. Thus, the masking property of the human ear is exploited by shaping the quantization error so that it has more energy in the formant regions where it will be masked by the strong signal energy present in these regions. The amount of weighting is controlled by the factors γ_1 and γ_2 .

[0052] The above traditional perceptual weighting filter 105 works well with telephone band signals. However, it was found that this traditional perceptual weighting filter 105 is not suitable for efficient perceptual weighting of wideband

signals. It was also found that the traditional perceptual weighting filter 105 has inherent limitations in modelling the formant structure and the required spectral tilt concurrently. The spectral tilt is more pronounced in wideband signals due to the wide dynamic range between low and high frequencies. The prior art has suggested to add a tilt filter into $W(z)$ in order to control the tilt and formant weighting of the wideband input signal separately.

5 [0053] A novel solution to this problem is, in accordance with the present invention, to introduce the preemphasis filter 103 at the input, compute the LP filter $A(z)$ based on the preemphasized speech $s(n)$, and use a modified filter $W(z)$ by fixing its denominator.

10 [0054] LP analysis is performed in module 104 on the preemphasized signal $s(n)$ to obtain the LP filter $A(z)$. Also, a new perceptual weighting filter 105 with fixed denominator is used. An example of transfer function for the perceptual weighting filter 104 is given by the following relation:

$$W(z) = A(z/\gamma_1) / (1 - \gamma_2 z^{-1})$$

15 where

$$0 < \gamma_2 < \gamma_1 \leq 1$$

20 [0055] A higher order can be used at the denominator. This structure substantially decouples the formant weighting from the tilt.

25 [0056] Note that because $A(z)$ is computed based on the preemphasized speech signal $s(n)$, the tilt of the filter $1/A(z/\gamma_1)$ is less pronounced compared to the case when $A(z)$ is computed based on the original speech. Since deemphasis is performed at the decoder end using a filter having the transfer function:

$$P^{-1}(z) = 1/(1 - \mu z^{-1}),$$

30 the quantization error spectrum is shaped by a filter having a transfer function $W^{-1}(z)P^{-1}(z)$. When γ_2 is set equal to μ , which is typically the case, the spectrum of the quantization error is shaped by a filter whose transfer function is $1/A(z/\gamma_1)$, with $A(z)$ computed based on the preemphasized speech signal. Subjective listening showed that this structure for achieving the error shaping by a combination of preemphasis and modified weighting filtering is very efficient for encoding wideband signals, in addition to the advantages of ease of fixed-point algorithmic implementation.

35 Pitch Analysis:

40 [0057] In order to simplify the pitch analysis, an open-loop pitch lag T_{OL} is first estimated in the open-loop pitch search module 106 using the weighted speech signal $s_w(n)$. Then the closed-loop pitch analysis, which is performed in closed-loop pitch search module 107 on a subframe basis, is restricted around the open-loop pitch lag T_{OL} which significantly reduces the search complexity of the LTP parameters T and b (pitch lag and pitch gain). Open-loop pitch analysis is usually performed in module 106 once every 10 ms (two subframes) using techniques well known to those of ordinary skill in the art.

45 [0058] The target vector x for LTP (Long Term Prediction) analysis is first computed. This is usually done by subtracting the zero-input response s_0 of weighted synthesis filter $W(z)/\hat{A}(z)$ from the weighted speech signal $s_w(n)$. This zero-input response s_0 is calculated by a zero-input response calculator 108. More specifically, the target vector x is calculated using the following relation:

$$x = s_w - s_0$$

50 where x is the N -dimensional target vector, s_w is the weighted speech vector in the subframe, and s_0 is the zero-input response of filter $W(z)/\hat{A}(z)$ which is the output of the combined filter $W(z)/\hat{A}(z)$ due to its initial states. The zero-input response calculator 108 is responsive to the quantized interpolated LP filter $\hat{A}(z)$ from the LP analysis, quantization and interpolation calculator 104 and to the initial states of the weighted synthesis filter $W(z)/\hat{A}(z)$ stored in memory module 111 to calculate the zero-input response s_0 (that part of the response due to the initial states as determined by setting the inputs equal to zero) of filter $W(z)/\hat{A}(z)$. This operation is well known to those of ordinary skill in the art and, accordingly, will not be further described.

55 [0059] Of course, alternative but mathematically equivalent approaches can be used to compute the target vector x .

[0060] A N -dimensional impulse response vector \mathbf{h} of the weighted synthesis filter $W(z)/\hat{A}(z)$ is computed in the impulse response generator 109 using the LP filter coefficients $A(z)$ and $\hat{A}(z)$ from module 104. Again, this operation is well known to those of ordinary skill in the art and, accordingly, will not be further described in the present specification.

[0061] The closed-loop pitch (or pitch codebook) parameters b , T and j are computed in the closed-loop pitch search module 107, which uses the target vector \mathbf{x} , the impulse response vector \mathbf{h} and the open-loop pitch lag T_{OL} as inputs. Traditionally, the pitch prediction has been represented by a pitch filter having the following transfer function:

$$1 / (1 - bz^{-T})$$

10 where b is the pitch gain and T is the pitch delay or lag. In this case, the pitch contribution to the excitation signal $u(n)$ is given by $bu(n-T)$, where the total excitation is given by

$$15 \quad u(n) = bu(n-T) + gc_k(n)$$

with g being the innovative codebook gain and $c_k(n)$ the innovative codevector at index k .

[0062] This representation has limitations if the pitch lag T is shorter than the subframe length N . In another representation, the pitch contribution can be seen as an pitch codebook containing the past excitation signal. Generally, each vector in the pitch codebook is a shift-by-one version of the previous vector (discarding one sample and adding a new sample). For pitch lags $T > N$, the pitch codebook is equivalent to the filter structure $(1/(1-bz^{-T}))$, and an pitch codebook vector $v_T(n)$ at pitch lag T is given by

$$25 \quad v_T(n) = u(n-T),$$

$n=0, \dots, N-1$.

For pitch lags T shorter than N , a vector $v_T(n)$ is built by repeating the available samples from the past excitation until the vector is completed (this is not equivalent to the filter structure).

30 [0063] In recent encoders, a higher pitch resolution is used which significantly improves the quality of voiced sound segments. This is achieved by oversampling the past excitation signal using polyphase interpolation filters. In this case, the vector $v_T(n)$ usually corresponds to an interpolated version of the past excitation, with pitch lag T being a non-integer delay (e.g. 50.25).

[0064] The pitch search consists of finding the best pitch lag T and gain b that minimize the mean squared weighted error E between the target vector \mathbf{x} and the scaled filtered past excitation. Error E being expressed as:

$$E = \|x - by_T\|^2$$

40 where \mathbf{y}_T is the filtered pitch codebook vector at pitch lag T :

$$45 \quad y_T(n) = v_T(n) * h(n) = \sum_{i=0}^n v_T(i)h(n-i),$$

$n=0, \dots, N-1$.

It can be shown that the error E is minimized by maximizing the search criterion

$$50 \quad C = \frac{x^T y_T}{\sqrt{y_T^T y_T}}$$

55 where t denotes vector transpose.

[0065] In the preferred embodiment of the present invention, a 1/3 subsample pitch resolution is used, and the pitch (pitch codebook) search is composed of three stages.

[0066] In the first stage, an open-loop pitch lag T_{OL} is estimated in open-loop pitch search module 106 in response

to the weighted speech signal $s_w(n)$. As indicated in the foregoing description, this open-loop pitch analysis is usually performed once every 10 ms (two subframes) using techniques well known to those of ordinary skill in the art.

[0067] In the second stage, the search criterion C is searched in the closed-loop pitch search module 107 for integer pitch lags around the estimated open-loop pitch lag T_{OL} (usually ± 5), which significantly simplifies the search procedure. A simple procedure is used for updating the filtered codevector \mathbf{y}_T without the need to compute the convolution for every pitch lag.

[0068] Once an optimum integer pitch lag is found in the second stage, a third stage of the search (module 107) tests the fractions around that optimum integer pitch lag.

[0069] When the pitch predictor is represented by a filter of the form $1/(1-bz^{-T})$, which is a valid assumption for pitch lags $T > N$, the spectrum of the pitch filter exhibits a harmonic structure over the entire frequency range, with a harmonic frequency related to $1/T$. In case of wideband signals, this structure is not very efficient since the harmonic structure in wideband signals does not cover the entire extended spectrum. The harmonic structure exists only up to a certain frequency, depending on the speech segment. Thus, in order to achieve efficient representation of the pitch contribution in voiced segments of wideband speech, the pitch prediction filter needs to have the flexibility of varying the amount of periodicity over the wideband spectrum.

[0070] A new method which achieves efficient modeling of the harmonic structure of the speech spectrum of wideband signals is disclosed in the present specification, whereby several forms of low pass filters are applied to the past excitation and the low pass filter with higher prediction gain is selected.

[0071] When subsample pitch resolution is used, the low pass filters can be incorporated into the interpolation filters used to obtain the higher pitch resolution. In this case, the third stage of the pitch search, in which the fractions around the chosen integer pitch lag are tested, is repeated for the several interpolation filters having different low-pass characteristics and the fraction and filter index which maximize the search criterion C are selected.

[0072] A simpler approach is to complete the search in the three stages described above to determine the optimum fractional pitch lag using only one interpolation filter with a certain frequency response, and select the optimum low-pass filter shape at the end by applying the different predetermined low-pass filters to the chosen pitch codebook vector \mathbf{v}_T and select the low-pass filter which minimizes the pitch prediction error. This approach is discussed in detail below.

[0073] Figure 3 illustrates a schematic block diagram of a preferred embodiment of the proposed approach.

[0074] In memory module 303, the past excitation signal $u(n)$, $n < 0$, is stored. The pitch codebook search module 301 is responsive to the target vector x , to the open-loop pitch lag T_{OL} and to the past excitation signal $u(n)$, $n < 0$, from memory module 303 to conduct a pitch codebook (pitch codebook) search minimizing the above-defined search criterion C. From the result of the search conducted in module 301, module 302 generates the optimum pitch codebook vector \mathbf{v}_T . Note that since a sub-sample pitch resolution is used (fractional pitch), the past excitation signal $u(n)$, $n < 0$, is interpolated and the pitch codebook vector \mathbf{v}_T corresponds to the interpolated past excitation signal. In this preferred embodiment, the interpolation filter (in module 301, but not shown) has a low-pass filter characteristic removing the frequency contents above 7000 Hz.

[0075] In a preferred embodiment, K filter characteristics are used; these filter characteristics could be low-pass or band-pass filter characteristics. Once the optimum codevector \mathbf{v}_T is determined and supplied by the pitch codevector generator 302, K filtered versions of \mathbf{v}_T are computed respectively using K different frequency shaping filters such as 305^(j), where $j=1, 2, \dots, K$. These filtered versions are denoted $\mathbf{v}_f^{(j)}$, where $j=1, 2, \dots, K$. The different vectors $\mathbf{V}_f^{(j)}$ are convolved in respective modules 304^(j), where $j=0, 1, 2, \dots, K$, with the impulse response \mathbf{h} to obtain the vectors $\mathbf{y}^{(j)}$, where $j=0, 1, 2, \dots, K$. To calculate the mean squared pitch prediction error for each vector $\mathbf{y}^{(j)}$, the value $\mathbf{y}^{(j)}$ is multiplied by the gain b by means of a corresponding amplifier 307^(j) and the value $b\mathbf{y}^{(j)}$ is subtracted from the target vector \mathbf{x} by means of a corresponding subtractor 308^(j). Selector 309 selects the frequency shaping filter 305^(j) which minimizes the mean squared pitch prediction error

45

$$e^{(j)} = \|x - b^{(j)} y^{(j)}\|^2,$$

$j=1, 2, \dots, K$

[0076] To calculate the mean squared pitch prediction error $e^{(j)}$ for each value of $\mathbf{y}^{(j)}$, the value $\mathbf{y}^{(j)}$ is multiplied by the gain b by means of a corresponding amplifier 307^(j) and the value $b^{(j)}\mathbf{y}^{(j)}$ is subtracted from the target vector \mathbf{x} by means of subtractors 308^(j). Each gain $b^{(j)}$ is calculated in a corresponding gain calculator 306^(j) in association with the frequency shaping filter at index j , using the following relationship:

55

$$b^{(j)} = x^t y^{(j)} / \|y^{(j)}\|^2.$$

[0076] In selector 309, the parameters b , T , and j are chosen based on \mathbf{v}_T or $\mathbf{v}_f^{(j)}$ which minimizes the mean squared

pitch prediction error e .

[0077] Referring back to Figure 1, the pitch codebook index T is encoded and transmitted to multiplexer 112. The pitch gain b is quantized and transmitted to multiplexer 112. With this new approach, extra information is needed to encode the index j of the selected frequency shaping filter in multiplexer 112. For example, if three filters are used ($j=0, 1, 2, 3$), then two bits are needed to represent this information. The filter index information j can also be encoded jointly with the pitch gain b .

Innovative codebook search:

[0078] Once the pitch, or LTP (Long Term Prediction) parameters b , T , and j are determined, the next step is to search for the optimum innovative excitation by means of search module 110 of Figure 1. First, the target vector \mathbf{x} is updated by subtracting the LTP contribution:

$$x' = x - b\mathbf{y}_T$$

where b is the pitch gain and \mathbf{y}_T is the filtered pitch codebook vector (the past excitation at delay T filtered with the selected low pass filter and convolved with the impulse response \mathbf{h} as described with reference to Figure 3).

[0079] The search procedure in CELP is performed by finding the optimum excitation codevector \mathbf{c}_k and gain g which minimize the mean-squared error between the target vector and the scaled filtered codevector

$$E = \| x' - gH\mathbf{c}_k \|^2$$

where \mathbf{H} is a lower triangular convolution matrix derived from the impulse response vector \mathbf{h} .

[0080] In the preferred embodiment of the present invention, the innovative codebook search is performed in module 110 by means of an algebraic codebook as described in US patents Nos: 5,444,816 (Adoul et al.) issued on August 22, 1995; 5,699,482 granted to Adoul et al., on December 17, 1997; 5,754,976 granted to Adoul et al., on May 19, 1998; and 5,701,392 (Adoul et al.) dated December 23, 1997.

[0081] Once the optimum excitation codevector \mathbf{c}_k and its gain g are chosen by module 110, the codebook index k and gain g are encoded and transmitted to multiplexer 112.

[0082] Referring to Figure 1, the parameters b , T , j , $\hat{A}(z)$, k and g are multiplexed through the multiplexer 112 before being transmitted through a communication channel.

Memory update:

[0083] In memory module 111 (Figure 1), the states of the weighted synthesis filter $W(z)/\hat{A}(z)$ are updated by filtering the excitation signal $\mathbf{u} = g\mathbf{c}_k + b\mathbf{v}_T$ through the weighted synthesis filter. After this filtering, the states of the filter are memorized and used in the next subframe as initial states for computing the zero-input response in calculator module 108.

[0084] As in the case of the target vector \mathbf{x} , other alternative but mathematically equivalent approaches well known to those of ordinary skill in the art can be used to update the filter states.

DECODER SIDE

[0085] The speech decoding device 200 of Figure 2 illustrates the various steps carried out between the digital input 222 (input stream to the demultiplexer 217) and the output sampled speech 223 (output of the adder 221).

[0086] Demultiplexer 217 extracts the synthesis model parameters from the binary information received from a digital input channel. From each received binary frame, the extracted parameters are:

- the short-term prediction parameters (STP) $\hat{A}(z)$ (once per frame);
- the long-term prediction (LTP) parameters T , b , and j (for each subframe); and
- the innovation codebook index k and gain g (for each subframe).

The current speech signal is synthesized based on these parameters as will be explained hereinbelow.

[0087] The innovative codebook 218 is responsive to the index k to produce the innovation codevector \mathbf{c}_k , which is

scaled by the decoded gain factor g through an amplifier 224. In the preferred embodiment, an innovative codebook 218 as described in the above mentioned US patent numbers 5,444,816; 5,699,482; 5,754,976; and 5,701,392 is used to represent the innovative codevector \mathbf{c}_k .

[0088] The generated scaled codevector $g\mathbf{c}_k$ at the output of the amplifier 224 is processed through a innovation filter 205.

Periodicity enhancement:

[0089] The generated scaled codevector at the output of the amplifier 224 is processed through a frequency-dependent pitch enhancer 205.

[0090] Enhancing the periodicity of the excitation signal u improves the quality in case of voiced segments. This was done in the past by filtering the innovation vector from the innovative codebook (fixed codebook) 218 through a filter in the form $1/(1-\epsilon bz^{-T})$ where ϵ is a factor below 0.5 which controls the amount of introduced periodicity. This approach is less efficient in case of wideband signals since it introduces periodicity over the entire spectrum. A new alternative approach, which is part of the present invention, is disclosed whereby periodicity enhancement is achieved by filtering the innovative codevector \mathbf{c}_k from the innovative (fixed) codebook through an innovation filter 205 ($F(z)$) whose frequency response emphasizes the higher frequencies more than lower frequencies. The coefficients of $F(z)$ are related to the amount of periodicity in the excitation signal u .

[0091] Many methods known to those skilled in the art are available for obtaining valid periodicity coefficients. For example, the value of gain b provides an indication of periodicity. That is, if gain b is close to 1, the periodicity of the excitation signal u is high, and if gain b is less than 0.5, then periodicity is low.

[0092] Another efficient way to derive the filter $F(z)$ coefficients used in a preferred embodiment, is to relate them to the amount of pitch contribution in the total excitation signal u . This results in a frequency response depending on the subframe periodicity, where higher frequencies are more strongly emphasized (stronger overall slope) for higher pitch gains. Innovation filter 205 has the effect of lowering the energy of the innovative codevector \mathbf{c}_k at low frequencies when the excitation signal u is more periodic, which enhances the periodicity of the excitation signal u at lower frequencies more than higher frequencies. Suggested forms for innovation filter 205 are

(1)

$$F(z)=1-\sigma z^{-1},$$

or

(2)

$$F(z)=-\alpha z+1-\alpha z^{-1}$$

where σ or α are periodicity factors derived from the level of periodicity of the excitation signal u .

[0093] The second three-term form of $F(z)$ is used in a preferred embodiment. The periodicity factor α is computed in the voicing factor generator 204. Several methods can be used to derive the periodicity factor α based on the periodicity of the excitation signal u . Two methods are presented below.

Method 1:

[0094] The ratio of pitch contribution to the total excitation signal u is first computed in voicing factor generator 204 by

$$R_p = \frac{b^2 v_T^t v_T}{u^t u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

where \mathbf{v}_T is the pitch codebook vector, b is the pitch gain, and \mathbf{u} is the excitation signal \mathbf{u} given at the output of the adder 219 by

$$5 \quad \mathbf{u} = g\mathbf{c}_k + b\mathbf{v}_T$$

[0095] Note that the term $b\mathbf{v}_T$ has its source in the pitch codebook (pitch codebook) 201 in response to the pitch lag T and the past value of \mathbf{u} stored in memory 203. The pitch codevector \mathbf{v}_T from the pitch codebook 201 is then processed through a low-pass filter 202 whose cut-off frequency is adjusted by means of the index j from the demultiplexer 217.

10 The resulting codevector \mathbf{v}_T is then multiplied by the gain b from the demultiplexer 217 through an amplifier 226 to obtain the signal $b\mathbf{v}_T$.

[0096] The factor a is calculated in voicing factor generator 204 by

$$15 \quad \alpha = qR_p$$

bounded by $\alpha < q$

where q is a factor which controls the amount of enhancement (q is set to 0.25 in this preferred embodiment).

20 **Method 2:**

[0097] Another method used in a preferred embodiment of the invention for calculating periodicity factor α is discussed below.

[0098] First, a voicing factor r_v is computed in voicing factor generator 204 by

$$25 \quad r_v = (E_v - E_c) / (E_v + E_c)$$

30 where E_v is the energy of the scaled pitch codevector $b\mathbf{v}_T$ and E_c is the energy of the scaled innovative codevector $g\mathbf{c}_k$. That is

$$35 \quad E_v = b^2 \mathbf{v}_T^t \mathbf{v}_T = b^2 \sum_{n=0}^{N-1} \mathbf{v}_T^2(n)$$

and

$$40 \quad E_c = g^2 \mathbf{c}_k^t \mathbf{c}_k = g^2 \sum_{n=0}^{N-1} \mathbf{c}_k^2(n) .$$

45 **[0099]** Note that the value of r_v lies between -1 and 1 (1 corresponds to purely voiced signals and -1 corresponds to purely unvoiced signals).

[0100] in this preferred embodiment, the factor α is then computed in voicing factor generator 204 by

$$50 \quad \alpha = 0.125(1 + r_v)$$

which corresponds to a value of 0 for purely unvoiced signals and 0.25 for purely voiced signals.

[0101] In the first, two-term form of $F(z)$, the periodicity factor σ can be approximated by using $\sigma = 2\alpha$ in methods 1 and 2 above. In such a case, the periodicity factor σ is calculated as follows in method 1 above:

55

$$\sigma = 2qR_p$$

5 bounded by $\sigma < 2q$.

[0102] In method 2, the periodicity factor σ is calculated as follows:

$$\sigma = 0.25 (1 + r_v).$$

[0103] The enhanced signal c_f is therefore computed by filtering the scaled innovative codevector $g c_k$ through the innovation filter 205 ($F(z)$).

[0104] The enhanced excitation signal u' is computed by the adder 220 as:

$$u' = c_f + b v_T$$

[0105] Note that this process is not performed at the encoder 100. Thus, it is essential to update the content of the pitch codebook 201 using the excitation signal u without enhancement to keep synchronism between the encoder 100 and decoder 200. Therefore, the excitation signal u is used to update the memory 203 of the pitch codebook 201 and the enhanced excitation signal u' is used at the input of the LP synthesis filter 206.

Synthesis and deemphasis

[0106] The synthesized signal s' is computed by filtering the enhanced excitation signal u' through the LP synthesis filter 206 which has the form $1/\hat{A}(z)$, where $\hat{A}(z)$ is the interpolated LP filter in the current subframe. As can be seen in Figure 2, the quantized LP coefficients $\hat{A}(z)$ on line 225 from demultiplexer 217 are supplied to the LP synthesis filter 206 to adjust the parameters of the LP synthesis filter 206 accordingly. The deemphasis filter 207 is the inverse of the preemphasis filter 103 of Figure 1. The transfer function of the deemphasis filter 207 is given by

$$D(z) = 1 / (1 - \mu z^{-1})$$

30 where μ is a preemphasis factor with a value located between 0 and 1 (a typical value is $\mu = 0.7$). A higher-order filter could also be used.

[0107] The vector s' is filtered through the deemphasis filter $D(z)$ (module 207) to obtain the vector s_d , which is passed through the high-pass filter 208 to remove the unwanted frequencies below 50 Hz and further obtain s_h .

Oversampling and high-frequency regeneration

[0108] The over-sampling module 209 conducts the inverse process of the down-sampling module 101 of Figure 1. In this preferred embodiment, oversampling converts from the 12.8 kHz sampling rate to the original 16 kHz sampling rate, using techniques well known to those of ordinary skill in the art. The oversampled synthesis signal is denoted \hat{s} . Signal \hat{s} is also referred to as the synthesized wideband intermediate signal.

[0109] The oversampled synthesis \hat{s} signal does not contain the higher frequency components which were lost by the downsampling process (module 101 of Figure 1) at the encoder 100. This gives a low-pass perception to the synthesized speech signal. To restore the full band of the original signal, a high frequency generation procedure is disclosed. This procedure is performed in modules 210 to 216, and adder 221, and requires input from voicing factor generator 204 (Figure 2).

[0110] In this new approach, the high frequency contents are generated by filling the upper part of the spectrum with a white noise properly scaled in the excitation domain, then converted to the speech domain, preferably by shaping it with the same LP synthesis filter used for synthesizing the down-sampled signal \hat{s} .

[0111] The high frequency generation procedure in accordance with the present invention is described hereinbelow.

[0112] The random noise generator 213 generates a white noise sequence w' with a flat spectrum over the entire frequency bandwidth, using techniques well known to those of ordinary skill in the art. The generated sequence is of length N' which is the subframe length in the original domain. Note that N is the subframe length in the down-sampled domain. In this preferred embodiment, $N=64$ and $N=80$ which correspond to 5 ms.

[0113] The white noise sequence is properly scaled in the gain adjusting module 214. Gain adjustment comprises the following steps. First, the energy of the generated noise sequence w' is set equal to the energy of the enhanced excitation signal u' computed by an energy computing module 210, and the resulting scaled noise sequence is given by

5

$$w(n) = w'(n) \sqrt{\frac{\sum_{n=0}^{N-1} u'^2(n)}{\sum_{n=0}^{N'-1} w'^2(n)}},$$

10

 $n=0, \dots, N-1$.

[0114] The second step in the gain scaling is to take into account the high frequency contents of the synthesized signal at the output of the voicing factor generator 204 so as to reduce the energy of the generated noise in case of voiced segments (where less energy is present at high frequencies compared to unvoiced segments). In this preferred embodiment, measuring the high frequency contents is implemented by measuring the tilt of the synthesis signal through a spectral tilt calculator 212 and reducing the energy accordingly. Other measurements such as zero crossing measurements can equally be used. When the tilt is very strong, which corresponds to voiced segments, the noise energy is further reduced. The tilt factor is computed in module 212 as the first correlation coefficient of the synthesis signal s_h and it is given by:

25

$$\text{tilt} = \frac{\sum_{n=1}^{N-1} s_h(n) s_h(n-1)}{\sum_{n=0}^{N-1} s_h^2(n)},$$

30

conditioned by $\text{tilt} \geq 0$ and $\text{tilt} \geq r_v$, where voicing factor r_v is given by

35

$$r_v = (E_v - E_c) / (E_v + E_c)$$

where E_v is the energy of the scaled pitch codevector bv_T and E_c is the energy of the scaled innovative codevector gc_k , as described earlier. Voicing factor r_v is most often less than tilt but this condition was introduced as a precaution against high frequency tones where the tilt value is negative and the value of r_v is high. Therefore, this condition reduces the noise energy for such tonal signals.

[0115] The tilt value is 0 in case of flat spectrum and 1 in case of strongly voiced signals, and it is negative in case of unvoiced signals where more energy is present at high frequencies.

[0116] Different methods can be used to derive the scaling factor g_t from the amount of high frequency contents. In this invention, two methods are given based on the tilt of signal described above.

Method 1:

[0117] The scaling factor g_t is derived from the tilt by

$$g_t = 1 - \text{tilt}$$

50

bounded by $0.2 \leq g_t \leq 1.0$

For strongly voiced signal where the tilt approaches 1, g_t is 0.2 and for strongly unvoiced signals g_t becomes 1.0.

Method 2:

[0118] The tilt factor g_t is first restricted to be larger or equal to zero, then the scaling factor is derived from the tilt by

$$5 \quad g_t = 10^{-0.8 \text{ tilt}}$$

[0119] The scaled noise sequence w_g produced in gain adjusting module 214 is therefore given by:

$$10 \quad w_g = g_t w.$$

[0120] When the tilt is close to zero, the scaling factor g_t is close to 1, which does not result in energy reduction. When the tilt value is 1, the scaling factor g_t results in a reduction of 12 dB in the energy of the generated noise.

15 [0121] Once the noise is properly scaled (w_g), it is brought into the speech domain using the spectral shaper 215. In the preferred embodiment, this is achieved by filtering the noise w_g through a bandwidth expanded version of the same LP synthesis filter used in the down-sampled domain ($1/\hat{A}(z^{0.8})$). The corresponding bandwidth expanded LP filter coefficients are calculated in spectral shaper 215.

20 [0122] The filtered scaled noise sequence w is then band-pass filtered to the required frequency range to be restored using the band-pass filter 216. In the preferred embodiment, the band-pass filter 216 restricts the noise sequence to the frequency range 5.6-7.2 kHz. The resulting band-pass filtered noise sequence z is added in adder 221 to the oversampled synthesized speech signal \hat{s} to obtain the final reconstructed sound signal s_{out} on the output 223.

25 [0123] Although the present invention has been described hereinabove by way of a preferred embodiment thereof, this embodiment can be modified at will, within the scope of the appended claims. Even though the preferred embodiment discusses the use of wideband speech signals, it will be obvious to those skilled in the art that the subject invention is also directed to other embodiments using wideband signals in general and that it is not necessarily limited to speech applications.

30 **Claims**

1. A device for enhancing periodicity of an excitation signal produced in relation to a pitch codevector and an innovative codevector for supplying a signal synthesis filter in view of synthesizing a wideband signal, said periodicity enhancing device comprising:

35 a) a factor generator (204) for calculating a periodicity factor related to the wideband signal; and
 b) an innovation filter (205) for filtering the innovative codevector in relation to said periodicity factor to thereby reduce energy of a low frequency portion of the innovative codevector and enhance periodicity of a low frequency portion of the excitation signal.

40 2. A periodicity enhancing device as defined in claim 1, wherein said factor generator comprises a means for calculating a periodicity factor in response to the pitch codevector and the innovative codevector.

45 3. A periodicity enhancing device as defined in claim 1, wherein said innovation filter has a transfer function of the form:

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

50 where α is a periodicity factor derived from a level of periodicity of the excitation signal.

55 4. A periodicity enhancing device as defined in claim 3, wherein said factor generator comprises a means for calculating said periodicity factor α using the relation:

$$\alpha = qR_p$$

bounded by $\alpha < q$
where q is an enhancement factor, and where

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

5

10

where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal.

- 5. A periodicity enhancing device as defined in claim 4, wherein said enhancement factor q is set to 0.25.
- 15. 6. A periodicity enhancing device as defined in claim 3, wherein said factor generator comprises a means for calculating said periodicity factor α using the relation:

$$\alpha = 0.125 (1 + r_v),$$

20

where

$$r_v = (E_v - E_c) / (E_v + E_c)$$

25

where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

- 7. A periodicity enhancing device as defined in claim 1, wherein said innovation filter has a transfer function of the form:

30

$$F(z)=1-\sigma z^{-1}$$

where σ is a periodicity factor derived from a level of periodicity of the excitation signal.

- 35. 8. A periodicity enhancing device as defined in claim 7, wherein said factor generator comprises a means for calculating said periodicity factor σ using the relation:

$$\sigma = 2qR_p$$

40

bounded by $\sigma < 2q$

where q is an enhancement factor, and where

45

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

50

where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal.

55

- 9. A periodicity enhancing device as defined in claim 8, wherein said enhancement factor q is set to 0.25.
- 10. A periodicity enhancing device as defined in claim 7, wherein said factor generator comprises a means for calcu-

EP 1 125 285 B1

lating said periodicity factor σ using the relation:

$$\sigma = 0.25 (1 + r_v),$$

5

where

$$r_v = (E_v - E_c) / (E_v + E_c)$$

10

where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

15

- 11.** A method for enhancing periodicity of an excitation signal produced in relation to a pitch codevector and an innovative codevector for supplying a signal synthesis filter in view of synthesizing a wideband signal, said periodicity enhancing method comprising the steps of:
- a) calculating a periodicity factor related to the wideband signal; and
 - b) filtering the innovative codevector in relation to said periodicity factor to thereby reduce energy of a low frequency portion of the innovative codevector and enhance periodicity of a low frequency portion of the excitation signal.

20

- 12.** A method for enhancing periodicity as defined in claim 10, wherein said factor generator comprises a means for calculating a periodicity factor in response to the pitch codevector and the innovative codevector.
- 13.** A method for enhancing periodicity as defined in claim 10, wherein said filtering comprises processing the innovation vector through an innovation filter having a transfer function of the form:

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

30

where α is a periodicity factor derived from a level of periodicity of the excitation signal.

35

- 14.** A method for enhancing periodicity as defined in claim 13, wherein said periodicity factor calculation comprises calculating said periodicity factor α using the relation:

35

$$\alpha = q R_p$$

40

bounded by $\alpha < q$

where q is an enhancement factor, and where

45

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

50

where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal.

55

- 15.** A method for enhancing periodicity as defined in claim 14, wherein said enhancement factor q is set to 0.25.
- 16.** A method for enhancing periodicity as defined in claim 13, wherein said periodicity factor calculation comprises calculating said periodicity factor α using the relation:

EP 1 125 285 B1

$$\alpha = 0.125 (1 + r_v),$$

where

5

$$r_v = (E_v - E_c) / (E_v + E_c)$$

where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

10

- 17.** A method for enhancing periodicity as defined in claim 11, wherein said filtering comprises processing the innovation vector through an innovation filter having a transfer function of the form:

15

$$F(z) = 1 - \sigma z^{-1}$$

where σ is a periodicity factor derived from a level of periodicity of the excitation signal.

20

- 18.** A method for enhancing periodicity as defined in claim 17, wherein said periodicity factor calculation comprises calculating said periodicity factor σ using the relation:

$$\sigma = 2qR_p$$

25

bounded by $\sigma < 2q$

where q is an enhancement factor, and where

30

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

35

where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal.

40

- 19.** A method for enhancing periodicity as defined in claim 18, wherein said enhancement factor q is set to 0.25.

45

- 20.** A method for enhancing periodicity defined in claim 17, wherein said periodicity factor calculation comprises calculating said periodicity factor σ using the relation:

45

$$\sigma = 0.25 (1 + r_v),$$

where

50

$$r_v = (E_v - E_c) / (E_v + E_c)$$

where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

55

- 21.** A decoder for producing a synthesized wideband signal, comprising:

- a) a signal fragmenting device for receiving an encoded wideband signal and extracting from said encoded wideband signal at least pitch codebook parameters, innovative codebook parameters, and synthesis filter coefficients;

- 5 b) an pitch codebook responsive to said pitch codebook parameters for producing a pitch codevector;
 c) an innovative codebook responsive to said innovative codebook parameters for producing an innovative codevector;
 d) a periodicity enhancing device as recited in claim 1 comprising said factor generator for calculating a periodicity factor related to the wideband signal, and said innovation filter for filtering the innovative codevector;
 e) a combiner circuit for combining said pitch codevector and said innovative codevector filtered by said innovation filter to thereby produce said periodicity enhanced excitation signal; and
 f) a signal synthesis filter for filtering said periodicity enhanced excitation signal in relation to said synthesis filter coefficients to thereby produce said synthesized wideband signal.

10 **22.** A decoder for producing a synthesized wideband signal as defined in claim 21, wherein said factor generator comprises a means for calculating a periodicity factor in response to the pitch codevector and the innovative codevector.

15 **23.** A decoder for producing a synthesized wideband signal as defined in claim 21, wherein said innovation filter has a transfer function of the form:

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

20 where α is a periodicity factor derived from a level of periodicity of the excitation signal.

25 **24.** A decoder for producing a synthesized wideband signal as defined in claim 23, wherein said factor generator comprises a means for calculating said periodicity factor α using the relation:

$$\alpha = qR_p$$

30 bounded by $\alpha < q$

where q is an enhancement factor, and where

$$35 \quad R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

40 where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal.

45 **25.** A decoder for producing a synthesized wideband signal as defined in claim 24, wherein said enhancement factor q is set to 0.25.

50 **26.** A decoder for producing a synthesized wideband signal as defined in claim 23, wherein said factor generator comprises a means for calculating said periodicity factor α using the relation:

$$\alpha = 0.125 (1 + r_v),$$

55 where

$$r_v = (E_v - E_c) / (E_v + E_c)$$

where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

27. A decoder for producing a synthesized wideband signal as defined in claim 21, wherein said innovation filter has a transfer function of the form:

5

$$F(z) = 1 - \sigma z^{-1}$$

where σ is a periodicity factor derived from a level of periodicity of the excitation signal.

- 10 28. A decoder for producing a synthesized wideband signal as defined in claim 27, wherein said factor generator comprises a means for calculating said periodicity factor σ using the relation:

$$\sigma = 2qR_p$$

15

bounded by $\sigma < 2q$
where q is an enhancement factor, and where

20

$$R_p = \frac{b^2 v_T^t v_T}{u^t u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

25

where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal.

- 30 29. A decoder for producing a synthesized wideband signal as defined in claim 28, wherein said enhancement factor q is set to 0.25.

- 35 30. A decoder for producing a synthesized wideband signal as defined in claim 27, wherein said factor generator comprises a means for calculating said periodicity factor σ using the relation:

35

$$\sigma = 0.25 (1 + r_v),$$

40

where

$$r_v = (E_v - E_c) / (E_v + E_c)$$

45

where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

45

31. A decoder for producing a synthesized wideband signal, comprising:

50

- a) a signal fragmenting device for receiving an encoded wideband signal and extracting from said encoded wideband signal at least pitch codebook parameters, innovative codebook parameters, and synthesis filter coefficients;
- b) a pitch codebook responsive to said pitch codebook parameters for producing a pitch codevector;
- c) an innovative codebook responsive to said innovative codebook parameters for producing an innovative codevector;
- d) a combiner circuit for combining said pitch codevector and innovative codevector to thereby produce an excitation signal; and
- e) a signal synthesis filter for filtering said excitation signal in relation to said synthesis filter coefficients to thereby produce said synthesized wideband signal;

the decoder further comprising a periodicity enhancing device as recited in claim 1 comprising a factor generator for calculating a periodicity factor related to the wideband signal, and said innovation filter for filtering the innovative codevector.

- 5 32. A decoder for producing a synthesized wideband signal as defined in claim 31, wherein said factor generator comprises a means for calculating a periodicity factor in response to the pitch codevector and the innovative codevector.
- 10 33. A decoder for producing a synthesized wideband signal as defined in claim 31, wherein said innovation filter has a transfer function of the form:

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

15 where α is a periodicity factor derived from a level of periodicity of the excitation signal.

- 20 34. A decoder for producing a synthesized wideband signal as defined in claim 33, wherein said factor generator comprises a means for calculating said periodicity factor α using the relation:

$$\alpha = qR_p$$

25 bounded by $\alpha < q$

where q is an enhancement factor, and where

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

35 where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal.

- 40 35. A decoder for producing a synthesized wideband signal as defined in claim 34, wherein said enhancement factor q is set to 0.25.
- 45 36. A decoder for producing a synthesized wideband signal as defined in claim 33, wherein said factor generator comprises a means for calculating said periodicity factor α using the relation:

$$\alpha = 0.125 (1 + r_v),$$

50 where

$$r_v = (E_v - E_c) / (E_v + E_c)$$

55 where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

37. A decoder for producing a synthesized wideband signal as defined in claim 31, wherein said innovation filter has a transfer function of the form:

$$F(z) = 1 - \sigma z^{-1}$$

where σ is a periodicity factor derived from a level of periodicity of the excitation signal.

38. A decoder for producing a synthesized wideband signal as defined in claim 37, wherein said factor generator comprises a means for calculating said periodicity factor σ using the relation:

5

$$\sigma = 2qR_p$$

bounded by $\sigma < 2q$

10 where q is an enhancement factor, and where

15

$$R_p = \frac{b^2 v_T^t v_T}{u^t u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

20

where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal.

39. A decoder for producing a synthesized wideband signal as defined in claim 38, wherein said enhancement factor 25 q is set to 0.25.

40. A decoder for producing a synthesized wideband signal as defined in claim 37, wherein said factor generator comprises a means for calculating said periodicity factor σ using the relation:

30

$$\sigma = 0.25 (1 + r_v),$$

where

35

$$r_v = (E_v - E_c) / (E_v + E_c)$$

where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

41. A cellular communication system for servicing a large geographical area divided into a plurality of cells, comprising:

- a) mobile transmitter/receiver units;
- b) cellular base stations respectively situated in said cells;
- c) a control terminal for controlling communication between the cellular base stations;
- d) a bidirectional wireless communication sub-system between each mobile unit situated in one cell and the cellular base station of said one cell, said bidirectional wireless communication sub-system comprising, in both the mobile unit and the cellular base station:
 - i) a transmitter including an encoder for encoding a wideband signal and a transmission circuit for transmitting the encoded wideband signal; and
 - ii) a receiver including a receiving circuit for receiving a transmitted encoded wideband signal and a decoder as recited in claim 21 for decoding the received encoded wideband signal.

42. A cellular communication system as defined in claim 41, wherein said factor generator comprises a means for calculating a periodicity factor in response to the pitch codevector and the innovative codevector.

55

43. A cellular communication system as defined in claim 41, wherein said innovation filter has a transfer function of the form:

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

where α is a periodicity factor derived from a level of periodicity of the excitation signal.

5

- 44.** A cellular communication system as defined in claim 43, wherein said factor generator comprises a means for calculating said periodicity factor α using the relation:

10

$$\alpha = qR_p$$

bounded by $\alpha < q$

where q is an enhancement factor, and where

15

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

20

where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal.

25

- 45.** A cellular communication system as defined in claim 44, wherein said enhancement factor q is set to 0.25.

- 46.** A cellular communication system as defined in claim 43, wherein said factor generator comprises a means for calculating said periodicity factor α using the relation:

30

$$\alpha = 0.125(1 + r_v),$$

where

35

$$r_v = (E_v - E_c) / (E_v + E_c)$$

where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

40

- 47.** A cellular communication system as defined in claim 41, wherein said innovation filter has a transfer function of the form:

$$F(z) = 1 - \sigma z^{-1}$$

45

where σ is a periodicity factor derived from a level of periodicity of the excitation signal.

- 48.** A cellular communication system as defined in claim 47, wherein said factor generator comprises a means for calculating said periodicity factor σ using the relation:

50

$$\sigma = 2qR_p$$

bounded by $\sigma < 2q$

55

where q is an enhancement factor, and where

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

10 where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal.

49. A cellular communication system as defined in claim 48, wherein said enhancement factor q is set to 0.25.

15 50. A cellular communication system as defined in claim 47, wherein said factor generator comprises a means for calculating said periodicity factor σ using the relation:

$$\sigma = 0.25 (1 + r_v),$$

20 where

$$r_v = (E_v - E_c) / (E_v + E_c)$$

25 where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

51. A cellular mobile transmitter/receiver unit comprising:

- 30 a) a transmitter including an encoder for encoding a wideband signal and a transmission circuit for transmitting the encoded wideband signal; and
 b) a receiver including a receiving circuit for receiving a transmitted encoded wideband signal and a decoder as recited in claim 21 for decoding the received encoded wideband signal.

35 52. A cellular mobile transmitter/receiver unit as defined in claim 51, wherein said factor generator comprises a means for calculating a periodicity factor in response to the pitch codevector and the innovative codevector.

53. A cellular mobile transmitter/receiver unit as defined in claim 51, wherein said innovation filter has a transfer function of the form:

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

40 where α is a periodicity factor derived from a level of periodicity of the excitation signal.

45 54. A cellular mobile transmitter/receiver unit as defined in claim 53, wherein said factor generator comprises a means for calculating said periodicity factor α using the relation:

$$\alpha = q R_p$$

50 bounded by $\alpha < q$
 where q is an enhancement factor, and where

5

$$R_p = \frac{b^2 v_T^t v_T}{u^t u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

10 where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal.

55. A cellular mobile transmitter/receiver unit as defined in claim 54, wherein said enhancement factor q is set to 0.25.
56. A cellular mobile transmitter/receiver unit as defined in claim 53, wherein said factor generator comprises a means
15 for calculating said periodicity factor α using the relation:

$$\alpha = 0.125 (1 + r_v),$$

20 where

$$r_v = (E_v - E_c) / (E_v + E_c)$$

25 where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

57. A cellular mobile transmitter/receiver unit as defined in claim 51, wherein said innovation filter has a transfer function
of the form:

30 $F(z)=1-\sigma z^{-1}$

where σ is a periodicity factor derived from a level of periodicity of the excitation signal.

- 35 58. A periodicity enhancing device as defined in claim 57, wherein said factor generator comprises a means for calculating
said periodicity factor σ using the relation:

$$\sigma = 2qR_p$$

40

bounded by $\sigma < 2q$

where q is an enhancement factor, and where

45

$$R_p = \frac{b^2 v_T^t v_T}{u^t u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

55 where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal.

59. A cellular mobile transmitter/receiver unit as defined in claim 58, wherein said enhancement factor q is set to 0.25.

60. A cellular mobile transmitter/receiver unit as defined in claim 57, wherein said factor generator comprises a means for calculating said periodicity factor σ using the relation:

$$5 \quad \sigma = 0.25 (1 + r_v),$$

where

$$10 \quad r_v = (E_v - E_c) / (E_v + E_c)$$

where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

15. 61. A cellular network element comprising:

- a) a transmitter including an encoder for encoding a wideband signal and a transmission circuit for transmitting the encoded wideband signal; and
- b) a receiver including a receiving circuit for receiving a transmitted encoded wideband signal and a decoder as recited in claim 21 for decoding the received encoded wideband signal.

20. 62. A cellular network element as defined in claim 61, wherein said factor generator comprises a means for calculating a periodicity factor in response to the pitch codevector and the innovative codevector.

25. 63. A cellular network element as defined in claim 61, wherein said innovation filter has a transfer function of the form:

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

30. where α is a periodicity factor derived from a level of periodicity of the excitation signal.

35. 64. A cellular network element as defined in claim 63, wherein said factor generator comprises a means for calculating said periodicity factor α using the relation:

$$\alpha = q R_p$$

40. bounded by $\alpha < q$

where q is an enhancement factor, and where

$$45. \quad R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

50. where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal.

55. 65. A cellular network element as defined in claim 64, wherein said enhancement factor q is set to 0.25.

66. A cellular network element as defined in claim 63, wherein said factor generator comprises a means for calculating said periodicity factor α using the relation:

$$\alpha = 0.125 (1 + r_v),$$

where

5

$$r_v = (E_v - E_c) / (E_v + E_c)$$

where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

10

67. A cellular network element as defined in claim 61, wherein said innovation filter has a transfer function of the form:

$$F(z)=1-\sigma z^{-1}$$

15

where σ is a periodicity factor derived from a level of periodicity of the excitation signal.

68. A cellular network element as defined in claim 67, wherein said factor generator comprises a means for calculating said periodicity factor σ using the relation:

20

$$\sigma = 2qR_p$$

bounded by $\sigma < 2q$

25

where q is an enhancement factor, and where

30

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

35

where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal.

69. A cellular network element as defined in claim 68, wherein said enhancement factor q is set to 0.25.

40

70. A cellular network element as defined in claim 67, wherein said factor generator comprises a means for calculating said periodicity factor σ using the relation:

$$\sigma = 0.25 (1 + r_v),$$

45

where

$$r_v = (E_v - E_c) / (E_v + E_c)$$

50

where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

55

71. A bidirectional wireless communication sub-system with a cellular communication system for servicing a large geographical area divided into a plurality of cells, comprising: mobile transmitter/receiver units; cellular base stations, respectively situated in said cells; and control terminal for controlling communication between the cellular base stations:

said bidirectional wireless communication sub-system between each mobile unit situated in one cell and the cellular base station of said one cell, said bidirectional wireless communication sub-system comprising, in both

the mobile unit and the cellular base station:

- 5 a) a transmitter including an encoder for encoding a wideband signal and a transmission circuit for transmitting the encoded wideband signal; and
- b) a receiver including a receiving circuit for receiving a transmitted encoded wideband signal and a decoder as recited in claim 21 for decoding the received encoded wideband signal.

72. A bidirectional wireless communication sub-system as defined in claim 71, wherein said factor generator comprises a means for calculating a periodicity factor in response to the pitch codevector and the innovative codevector.

10 73. A bidirectional wireless communication sub-system as defined in claim 71, wherein said innovation filter has a transfer function of the form:

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

15 where α is a periodicity factor derived from a level of periodicity of the excitation signal.

20 74. A bidirectional wireless communication sub-system as defined in claim 73, wherein said factor generator comprises a means for calculating said periodicity factor α using the relation:

$$\alpha = qR_p$$

25 bounded by $\alpha < q$

where q is an enhancement factor, and where

$$30 \quad R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

35 where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal.

40 75. A bidirectional wireless communication sub-system as defined in claim 74, wherein said enhancement factor q is set to 0.25.

45 76. A bidirectional wireless communication sub-system as defined in claim 73, wherein said factor generator comprises a means for calculating said periodicity factor α using the relation:

$$\alpha = 0.125 (1 + r_v),$$

50 where

$$r_v = (E_v - E_c) / (E_v + E_c)$$

55 where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

77. A bidirectional wireless communication sub-system as defined in claim 71, wherein said innovation filter has a transfer function of the form:

$$F(z)=1-\sigma z^{-1}$$

where σ is a periodicity factor derived from a level of periodicity of the excitation signal.

5

78. A bidirectional wireless communication sub-system as defined in claim 77, wherein said factor generator comprises a means for calculating said periodicity factor σ using the relation:

10

$$\sigma = 2qR_p$$

bounded by $\sigma < 2q$

where q is an enhancement factor, and where

15

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

25

where v_T is the pitch codevector, b is a pitch gain, N is a subframe length, and u is the excitation signal.

30

79. A bidirectional wireless communication sub-system as defined in claim 78, wherein said enhancement factor q is set to 0.25.
80. A bidirectional wireless communication sub-system as defined in claim 77, wherein said factor generator comprises a means for calculating said periodicity factor σ using the relation:

35

$$\sigma = 0.25 (1 + r_v),$$

where

40

$$r_v = (E_v - E_c) / (E_v + E_c)$$

where E_v is the energy of the pitch codevector and E_c is the energy of the innovative codevector.

45

Patentansprüche

50

1. Vorrichtung zum Verbessern der Periodizität eines Erregungssignals, das in bezug auf einen Tonhöhen-Codevektor und einen innovativen Codevektor erzeugt wird, um ein Signalsynthetisierungsfilter im Hinblick auf die Synthesierung eines Breitbandsignals zu versorgen, wobei die Periodizitätsverbesserungsvorrichtung umfaßt:
 - a) einen Faktorgenerator (204) zum Berechnen eines Periodizitätsfaktors, der mit dem Breitbandsignal in Beziehung steht; und
 - b) ein Innovationsfilter (205) zum Filtern des innovativen Codeektors in bezug auf den Periodizitätsfaktor, um dadurch die Energie eines niederfrequenten Abschnitts des innovativen Codeektors zu reduzieren und die Periodizität eines niederfrequenten Abschnitts des Erregungssignals zu verbessern.
2. Periodizitätsverbesserungsvorrichtung nach Anspruch 1, bei der der Faktorgenerator eine Einrichtung zum Berechnen eines Periodizitätsfaktors in Reaktion auf den Tonhöhen-Codevektor und den innovativen Codevektor

umfaßt.

3. Periodizitätsverbesserungsvorrichtung nach Anspruch 1, bei der das Innovationsfilter eine Übertragungsfunktion der folgenden Form besitzt:

5

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

wobei α ein Periodizitätsfaktor ist, der von einem Periodizitätsniveau des Erregungssignals abgeleitet ist.

10

4. Periodizitätsverbesserungsvorrichtung nach Anspruch 3, bei der der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors α unter Verwendung der folgenden Beziehung umfaßt:

15

$$\alpha = qR_p,$$

beschränkt durch $\alpha < q$

wobei q ein Verbesserungsfaktor ist und wobei

20

$$R_p = \frac{b^2 \mathbf{v}_T^t \mathbf{v}_T}{\mathbf{u}^t \mathbf{u}} = \frac{b^2 \sum_{n=0}^{N-1} \mathbf{v}_T^2(n)}{\sum_{n=0}^{N-1} \mathbf{u}^2(n)}$$

25

wobei \mathbf{v}_T der Tonhöhen-Codevektor ist, b eine Tonhöhenverstärkung ist, N eine Unterrahmenlänge ist und \mathbf{u} das Erregungssignal ist.

30

5. Periodizitätsverbesserungsvorrichtung nach Anspruch 4, bei der der Verbesserungsfaktor q auf 0,25 gesetzt ist.

35

6. Periodizitätsverbesserungsvorrichtung nach Anspruch 3, bei der der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors α unter Verwendung der folgenden Beziehung umfaßt:

$$\alpha = 0,125(1 + r_v),$$

40

wobei

$$r_v = (E_v - E_c)/(E_v + E_c)$$

45

wobei E_v die Energie des Tonhöhen-Codevektors ist und E_c die Energie des innovativen Codevektors ist.

7. Periodizitätsverbesserungsvorrichtung nach Anspruch 1, bei der das Innovationsfilter eine Übertragungsfunktion der folgenden Form besitzt:

50

$$F(z) = 1 - \sigma z^{-1}$$

wobei σ ein Periodizitätsfaktor ist, der von einem Periodizitätsniveau des Erregungssignals abgeleitet ist.

55

8. Periodizitätsverbesserungsvorrichtung nach Anspruch 7, bei der der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors σ unter Verwendung der folgenden Beziehung umfaßt:

EP 1 125 285 B1

$$\sigma = 2qR_p,$$

beschränkt durch $\sigma < 2q$

5 wobei q ein Verbesserungsfaktor ist und wobei

$$10 R_p = \frac{b^2 \mathbf{v}_T^t \mathbf{v}_T}{\mathbf{u}^t \mathbf{u}} = \frac{b^2 \sum_{n=0}^{N-1} \mathbf{v}_T^2(n)}{\sum_{n=0}^{N-1} \mathbf{u}^2(n)}$$

15 wobei \mathbf{v}_T der Tonhöhen-Codevektor ist, b eine Tonhöhenverstärkung ist, N eine Unterrahmenlänge ist und \mathbf{u} das Erregungssignal ist.

9. Periodizitätsverbesserungsvorrichtung nach Anspruch 8, bei der der Verbesserungsfaktor q auf 0,25 gesetzt ist.
 20 10. Periodizitätsverbesserungsvorrichtung nach Anspruch 7, bei der der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors σ unter Verwendung der folgenden Beziehung umfaßt:

$$\sigma = 0,25(1 + r_v),$$

25

wobei

$$r_v = (E_v - E_c)/(E_v + E_c)$$

30

wobei E_v die Energie des Tonhöhen-Codevektors ist und E_c die Energie des innovativen Codevektors ist.

11. Verfahren zum Verbessern der Periodizität eines Erregungssignals, das in bezug auf einen Tonhöhen-Codevektor und auf einen innovativen Codevektor erzeugt wird, um ein Signalsynthetisierungsfilter im Hinblick auf die Synthesierung eines Breitbandsignals zu versorgen, wobei das Periodizitätsverbesserungsverfahren die folgenden Schritte umfaßt:

- a) Berechnen eines Periodizitätsfaktors, der mit dem Breitbandsignal in Beziehung steht; und
 40 b) Filtern des innovativen Codevektors in bezug auf den Periodizitätsfaktor, um dadurch die Energie eines niederfrequenten Abschnitts des innovativen Codevektors zu reduzieren und um die Periodizität eines niederfrequenten Abschnitts des Erregungssignals zu verbessern.
 12. Verfahren zum Verbessern der Periodizität nach Anspruch 11, bei dem der Berechnen Schritt das Berechnen eines Periodizitätfaktors in Reaktion auf den Tonhöhen-Codevektor und den innovativen Codevektor umfaßt.
 45 13. Verfahren zum Verbessern der Periodizität nach Anspruch 11, bei dem die Filterung das Verarbeiten des Innovationsvektors durch ein Innovationsfilter umfaßt, das eine Übertragungsfunktion der folgenden Form besitzt:

$$50 F(z) = -\alpha z + 1 - \alpha z^{-1}$$

wobei α ein Periodizitätsfaktor ist, der von einem Periodizitätsniveau des Erregungssignals abgeleitet wird.

14. Verfahren zum Verbessern der Periodizität nach Anspruch 13, bei dem die Periodizitätsfaktor-Berechnung das Berechnen des Periodizitätsfaktors α unter Verwendung der folgenden Beziehung umfaßt:

$$\alpha = qR_p,$$

EP 1 125 285 B1

beschränkt durch $\alpha < q$,
wobei q ein Verbesserungsfaktor ist und wobei

$$R_p = \frac{b^2 \mathbf{v}_T^t \mathbf{v}_T}{\mathbf{u}^t \mathbf{u}} = \frac{b^2 \sum_{n=0}^{N-1} \mathbf{v}_T^2(n)}{\sum_{n=0}^{N-1} \mathbf{u}^2(n)}$$

10

wobei \mathbf{v}_T der Tonhöhen-Codevektor ist, b eine Tonhöhenverstärkung ist, N eine Unterrahmenlänge ist und \mathbf{u} das Erregungssignal ist.

- 15 15. Verfahren zum Verbessern der Periodizität nach Anspruch 14, bei dem der Verbesserungsfaktor q auf 0,25 gesetzt ist.
16. Verfahren zum Verbessern der Periodizität nach Anspruch 13, bei dem die Periodizitätsfaktor-Berechnung das Berechnen des Periodizitätsfaktors α unter Verwendung der folgenden Beziehung umfaßt:

20

$$\alpha = 0,125(1 + r_v),$$

wobei

25

$$r_v = (E_v - E_c)/(E_v + E_c)$$

wobei E_v die Energie des Tonhöhen-Codevektors ist und E_c die Energie des innovativen Codevektors ist.

30

17. Verfahren zum Verbessern der Periodizität nach Anspruch 11, bei dem die Filterung die Verarbeitung des Innovationsvektors durch ein Innovationsfilter umfaßt, das eine Übertragungsfunktion der folgenden Form besitzt:

35

$$F(z) = \frac{1}{1 - \sigma z^{-1}}$$

wobei σ ein Periodizitätsfaktor ist, der von einem Periodizitätsniveau des Erregungssignals abgeleitet wird.

- 40 18. Verfahren zum Verbessern der Periodizität nach Anspruch 17, bei dem die Periodizitätsfaktor-Berechnung das Berechnen des Periodizitätsfaktors σ unter Verwendung der folgenden Beziehung umfaßt:

$$\sigma = 2qR_p,$$

45

beschränkt durch $\sigma < 2q$,
wobei q ein Verstärkungsfaktor ist und wobei

50

$$R_p = \frac{b^2 \mathbf{v}_T^t \mathbf{v}_T}{\mathbf{u}^t \mathbf{u}} = \frac{b^2 \sum_{n=0}^{N-1} \mathbf{v}_T^2(n)}{\sum_{n=0}^{N-1} \mathbf{u}^2(n)}$$

55

EP 1 125 285 B1

wobei \mathbf{v}_T der Tonhöhen-Codevektor ist, b eine Tonhöhenverstärkung ist, N eine Unterrahmenlänge ist und \mathbf{u} das Erregungssignal ist.

- 5 19. Verfahren zum Verbessern der Periodizität nach Anspruch 18, bei dem der Verstärkungsfaktor q auf 0,25 gesetzt ist.

- 10 20. Verfahren zum Verbessern der Periodizität nach Anspruch 17, bei dem die Periodizitätsfaktor-Berechnung das Berechnen des Periodizitätsfaktors σ unter Verwendung der folgenden Beziehung umfaßt:

$$\sigma = 0,25(1 + r_v),$$

wobei

$$r_v = (E_v - E_c)/(E_v + E_c)$$

wobei E_v die Energie des Tonhöhen-Codevektors ist und E_c die Energie des innovativen Codevektors ist.

- 20 21. Decodierer zum Erzeugen eines synthetisierten Breitbandsignals, der umfaßt:

a) eine Signalfragmentierungsvorrichtung zum Empfangen eines codierten Breitbandsignals und Extrahieren wenigstens von Parametern für ein Tonhöhen-Codebuch, Parametern für ein innovatives Codebuch und Synthesizerfilter-Koeffizienten aus dem codierten Breitbandsignal;

- 25 b) ein Tonhöhen-Codebuch, das in Reaktion auf die Parameter für ein Tonhöhen-Codebuch einen Tonhöhen-Codevektor erzeugt;

c) ein innovatives Codebuch, das in Reaktion auf Parameter für ein innovatives Codebuch einen innovativen Codevektor erzeugt;

- 30 d) eine Periodizitätsverbesserungsvorrichtung nach Anspruch 1, die den Faktorgenerator zum Berechnen eines mit dem Breitbandsignal in Beziehung stehenden Periodizitätsfaktors und das Innovationsfilter zum Filtern des innovativen Codevektors umfaßt;

e) eine Kombinationsschaltung zum Kombinieren des Tonhöhen-Codevektors und des innovativen Codevektors, der durch das Innovationsfilter gefiltert wird, um dadurch das Erregungssignal mit verbesserter Periodizität zu erzeugen; und

- 35 f) ein Signalsynthesizerfilter zum Filtern des Erregungssignals mit verbesserter Periodizität in bezug auf die Synthesizerfilter-Koeffizienten, um dadurch das synthetisierte Breitbandsignal zu erzeugen.

22. Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 21, bei dem der Faktorgenerator eine Einrichtung zum Berechnen eines Periodizitätsfaktors in Reaktion auf den Tonhöhen-Codevektor und den innovativen Codevektor umfaßt.

- 40 23. Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 21, bei dem das Innovationsfilter eine Übertragungsfunktion der folgenden Form besitzt:

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

wobei α ein Periodizitätsfaktor ist, der von einem Periodizitätsniveau des Erregungssignals abgeleitet ist.

- 50 24. Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 23, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors α unter Verwendung der folgenden Beziehung umfaßt:

$$\alpha = qR_p,$$

55

beschränkt durch $\alpha < q$

wobei q ein Verstärkungsfaktor ist und wobei

$$R_p = \frac{b^2 \mathbf{v}_T^t \mathbf{v}_T}{\mathbf{u}^t \mathbf{u}} = \frac{b^2 \sum_{n=0}^{N-1} \mathbf{v}_T^2(n)}{\sum_{n=0}^{N-1} \mathbf{u}^2(n)}$$

5

wobei \mathbf{v}_T der Tonhöhen-Codevektor ist, b eine Tonhöhenverstärkung ist, N eine Unterrahmenlänge ist und \mathbf{u} das Erregungssignal ist.

- 10
- 25.** Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 24, bei dem der Verstärkungsfaktor q auf 0,25 gesetzt ist.
- 26.** Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 23, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors α unter Verwendung der folgenden Beziehung umfaßt:

$$\alpha = 0,125(1 + r_v),$$

20

wobei

$$r_v = (E_v - E_c)/(E_v + E_c)$$

25 wobei E_v die Energie des Tonhöhen-Codevektors ist und E_c die Energie des innovativen Codevektors ist.

- 27.** Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 21, bei dem das Innovationsfilter eine Übertragungsfunktion der folgenden Form hat:

30

$$F(z) = 1 - \sigma z^{-1}$$

wobei σ ein Periodizitätsfaktor ist, der von einem Periodizitätsniveau des Erregungssignals abgeleitet ist.

35

- 28.** Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 27, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors σ unter Verwendung der folgenden Beziehung umfaßt:

40

$$\sigma = 2qR_p,$$

beschränkt durch $\sigma < 2q$,
wobei q ein Verstärkungsfaktor ist und wobei

45

$$R_p = \frac{b^2 \mathbf{v}_T^t \mathbf{v}_T}{\mathbf{u}^t \mathbf{u}} = \frac{b^2 \sum_{n=0}^{N-1} \mathbf{v}_T^2(n)}{\sum_{n=0}^{N-1} \mathbf{u}^2(n)}$$

50

wobei \mathbf{v}_T der Tonhöhen-Codevektor ist, b eine Tonhöhenverstärkung ist, N eine Unterrahmenlänge ist und \mathbf{u} das Erregungssignal ist.

55

- 29.** Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 28, bei dem der Verstärkungsfaktor q auf 0,25 gesetzt ist.

EP 1 125 285 B1

- 30.** Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 27, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors σ unter Verwendung der folgenden Beziehung umfaßt:

5 $\sigma = 0,25(1 + r_v)$, wobei

$$r_v = (E_V - E_c)/(E_V + E_c)$$

10 wobei E_V die Energie des Tonhöhen-Codevektors ist und E_c die Energie des innovativen Codevektors ist.

- 31.** Decodierer zum Erzeugen eines synthetisierten Breitbandsignals, der umfaßt:

- 15 a) eine Signalfragmentierungsvorrichtung zum Empfangen eines codierten Breitbandsignals und Extrahieren wenigstens von Parametern für ein Tonhöhen-Codebuch, Parametern für ein innovatives Codebuch und Synthetisierungsfilter-Koeffizienten aus dem codierten Breitbandsignal;
 b) ein Tonhöhen-Codebuch, das in Reaktion auf die Parameter für ein Tonhöhen-Codebuch einen Tonhöhen-Codevektor erzeugt;
 c) ein innovatives Codebuch, das in Reaktion auf die Parameter für ein innovatives Codebuch einen innovativen Codevektor erzeugt;
 20 d) eine Kombinationsschaltung zum Kombinieren des Tonhöhen-Codevektors und des innovativen Codevektors, um dadurch ein Erregungssignal zu erzeugen; und
 e) ein Signalsynthetisierungsfilter zum Filtern des Erregungssignals in bezug auf die Synthetisierungsfilter-Koeffizienten, um dadurch das synthetisierte Breitbandsignal zu erzeugen;

25 wobei der Decodierer ferner eine Periodizitätsverbesserungsvorrichtung nach Anspruch 1 umfaßt, die einen Faktorgenerator zum Berechnen eines auf das Breitbandsignal bezogenen Periodizitätsfaktors und das Innovationsfilter zum Filtern des innovativen Codevektors umfaßt.

30 **32.** Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 31, bei dem der Faktorgenerator eine Einrichtung zum Berechnen eines Periodizitätsfaktors in Reaktion auf den Tonhöhen-Codevektor und den innovativen Codevektor umfaßt.

35 **33.** Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 31, bei dem das Innovationsfilter eine Übertragungsfunktion der folgenden Form besitzt:

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

40 wobei α ein Periodizitätsfaktor ist, der von einem Periodizitätsniveau des Erregungssignals abgeleitet wird.

- 34.** Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 33, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors α unter Verwendung der folgenden Beziehung umfaßt:

45 $\alpha = qR_p$,

beschränkt durch $\alpha < q$,

wobei q ein Verstärkungsfaktor ist und wobei

50

55
$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

EP 1 125 285 B1

wobei \mathbf{v}_T der Tonhöhen-Codevektor ist, b eine Tonhöhenverstärkung ist, N eine Unterrahmenlänge ist und \mathbf{u} das Erregungssignal ist.

35. Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 34, bei dem der Verstärkfaktor q auf 0,25 gesetzt ist.

36. Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 33, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors α unter Verwendung der folgenden Beziehung umfaßt:

$$10 \quad \alpha = 0,125(1 + r_v),$$

wobei

$$15 \quad r_v = (E_v - E_c)/(E_v + E_c)$$

wobei E_v die Energie des Tonhöhen-Codevektors ist und E_c die Energie des innovativen Codevektors ist.

- 20 37. Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 31, bei dem das Innovationsfilter eine Übertragungsfunktion der folgenden Form besitzt:

$$F(z) = 1 - \sigma z^{-1}$$

25 wobei σ ein Periodizitätsfaktor ist, der von einem Periodizitätsniveau des Erregungssignals abgeleitet wird.

38. Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 37, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors σ unter Verwendung der folgenden Beziehung umfaßt:

$$30 \quad \sigma = 2qR_p,$$

beschränkt durch $\sigma < 2q$,

35 wobei q ein Verbesserungsfaktor ist und wobei

$$40 \quad R_p = \frac{b^2 \mathbf{v}_T^t \mathbf{v}_T}{\mathbf{u}^t \mathbf{u}} = \frac{b^2 \sum_{n=0}^{N-1} \mathbf{v}_T^2(n)}{\sum_{n=0}^{N-1} \mathbf{u}^2(n)}$$

45 wobei \mathbf{v}_T der Tonhöhen-Codevektor ist, b eine Tonhöhenverstärkung ist, N eine Unterrahmenlänge ist und \mathbf{u} das Erregungssignal ist.

39. Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 38, bei dem der Verbesserungsfaktor q auf 0,25 gesetzt ist.

- 50 40. Decodierer zum Erzeugen eines synthetisierten Breitbandsignals nach Anspruch 37, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors σ unter Verwendung der folgenden Beziehung umfaßt:

$$55 \quad \sigma = 0,25(1 + r_v),$$

wobei

$$r_v = (E_v - E_c)/(E_v + E_c)$$

wobei E_v die Energie des Tonhöhen-Codevektors ist und E_c die Energie des innovativen Codevektors ist.

5

- 41.** Zellenkommunikationssystem zum Bedienen eines großen geographischen Gebiets, das in mehrere Zellen unterteilt ist, wobei das System umfaßt:

10

- a) mobile Sender/Empfänger-Einheiten;
 - b) Zellenbasisstationen, die sich jeweils in den Zellen befinden;
 - c) ein Steuerendgerät zum Steuern der Kommunikation zwischen den Zellenbasisstationen;
 - d) ein bidirektionales drahtloses Kommunikationsundersystem zwischen jeder Mobileinheit, die sich in einer Zelle befindet, und der Zellenbasisstation der einen Zelle, wobei das bidirektionale drahtlose Kommunikationsundersystem sowohl in der Mobileinheit als auch in der Zellenbasisstation umfaßt:
- 15
- i) einen Sender, der einen Codierer zum Codieren eines Breitbandsignals und eine Sendeschaltung zum Senden des codierten Breitbandsignals enthält; und
 - ii) einen Empfänger, der eine Empfängerschaltung zum Empfangen eines gesendeten codierten Breitbandsignals und einen Decodierer nach Anspruch 21 zum Decodieren des empfangenen codierten Breitbandsignals enthält.
- 20

- 42.** Zellenkommunikationssystem nach Anspruch 41, bei dem der Faktorgenerator eine Einrichtung zum Berechnen eines Periodizitätsfaktors in Reaktion auf den Tonhöhen-Codevektor und den innovativen Codevektor umfaßt.

25

- 43.** Zellenkommunikationssystem nach Anspruch 41, bei dem das Innovationsfilter eine Übertragungsfunktion der folgenden Form besitzt:

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

30

wobei α ein Periodizitätsfaktor ist, der von einem Periodizitätsniveau des Erregungssignals abgeleitet ist.

35

- 44.** Zellenkommunikationssystem nach Anspruch 43, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors α unter Verwendung der folgenden Beziehung umfaßt:

$$\alpha = qR_p,$$

40

beschränkt durch $\alpha < q$

wobei q ein Verbesserungsfaktor ist und wobei

45

$$R_p = \frac{b^2 \mathbf{v}_T^T \mathbf{v}_T}{\mathbf{u}^T \mathbf{u}} = \frac{b^2 \sum_{n=0}^{N-1} \mathbf{v}_T^2(n)}{\sum_{n=0}^{N-1} \mathbf{u}^2(n)}$$

50

wobei \mathbf{v}_T der Tonhöhen-Codevektor ist, b eine Tonhöhenverstärkung ist, N eine Unterrahmenlänge ist und \mathbf{u} das Erregungssignal ist.

55

- 45.** Zellenkommunikationssystem nach Anspruch 44, bei dem der Verbesserungsfaktor q auf 0,25 gesetzt ist.

- 46.** Zellenkommunikationssystem nach Anspruch 43, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors α unter Verwendung der folgenden Beziehung umfaßt:

EP 1 125 285 B1

$$\alpha = 0,125(1 + r_v),$$

wobei

5

$$r_v = (E_v - E_c)/(E_v + E_c)$$

wobei E_v die Energie des Tonhöhen-Codevektors ist und E_c die Energie des innovativen Codevektors ist.

10

- 47.** Zellenkommunikationssystem nach Anspruch 41, bei dem das Innovationsfilter eine Übertragungsfunktion der folgenden Form besitzt:

15

$$F(z) = 1 - \sigma z^{-1}$$

wobei σ ein Periodizitätsfaktor ist, der von einem Periodizitätsniveau des Erregungssignals abgeleitet ist.

20

- 48.** Zellenkommunikationssystem nach Anspruch 47, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors σ unter Verwendung der folgenden Beziehung umfaßt:

$$\sigma = 2qR_p,$$

25

beschränkt durch $\sigma < 2q$,

wobei q ein Verbesserungsfaktor ist und wobei

30

$$R_p = \frac{b^2 \mathbf{v}_T^t \mathbf{v}_T}{\mathbf{u}^t \mathbf{u}} = \frac{b^2 \sum_{n=0}^{N-1} \mathbf{v}_T^2(n)}{\sum_{n=0}^{N-1} \mathbf{u}^2(n)}$$

35

wobei \mathbf{v}_T der Tonhöhen-Codevektor ist, b eine Tonhöhenverstärkung ist, N eine Unterrahmenlänge ist und \mathbf{u} das Erregungssignal ist.

40

- 49.** Zellenkommunikationssystem nach Anspruch 48, bei dem der Verbesserungsfaktor q auf 0,25 gesetzt ist.

45

- 50.** Zellenkommunikationssystem nach Anspruch 47, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors σ unter Verwendung der folgenden Beziehung umfaßt:

45

$$\sigma = 0,25(1 + r_v),$$

wobei

50

$$r_v = (E_v - E_c)/(E_v + E_c)$$

wobei E_v die Energie des Tonhöhen-Codevektors ist und E_c die Energie des innovativen Codevektors ist.

55

- 51.** Mobile Zellen-Sender/Empfänger-Einheit, die umfaßt:

- a) einen Sender, der einen Codierer zum Codieren eines Breitbandsignals und eine Sendeschaltung zum Senden des codierten Breitbandsignals enthält; und
- b) einen Empfänger, der eine Empfängerschaltung zum Empfangen eines gesendeten codierten Breitband-

EP 1 125 285 B1

signals und einen Decodierer nach Anspruch 21 zum Decodieren des empfangenen decodierten Breitbandsignals enthält.

- 5 **52.** Mobile Zellen-Sender/Empfänger-Einheit nach Anspruch 51, bei der der Faktorgenerator eine Einrichtung zum Berechnen eines Periodizitätsfaktors in Reaktion auf den Tonhöhen-Codevektor und den innovativen Codevektor umfaßt.

- 10 **53.** Mobile Zellen-Sender/Empfänger-Einheit nach Anspruch 51, bei der das Innovationsfilter eine Übertragungsfunktion der folgenden Form besitzt:

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

wobei α ein Periodizitätsfaktor ist, der von dem Periodizitätsniveau des Erregungssignals abgeleitet wird.

- 15 **54.** Mobile Zellen-Sender/Empfänger-Einheit nach Anspruch 53, bei der der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors α unter Verwendung der folgenden Beziehung umfaßt:

$$\alpha = qR_p,$$

20 beschränkt durch $\alpha < q$

wobei q ein Verbesserungsfaktor ist und wobei

$$30 R_p = \frac{b^2 \mathbf{v}_T^t \mathbf{v}_T}{\mathbf{u}^t \mathbf{u}} = \frac{b^2 \sum_{n=0}^{N-1} \mathbf{v}_T^2(n)}{\sum_{n=0}^{N-1} \mathbf{u}^2(n)}$$

35 wobei \mathbf{v}_T der Tonhöhen-Codevektor ist, b eine Tonhöhenverstärkung ist, N eine Unterrahmenlänge ist und \mathbf{u} das Erregungssignal ist.

- 40 **55.** Mobile Zellen-Sender/Empfänger-Einheit nach Anspruch 54, bei der der Verbesserungsfaktor q auf 0,25 gesetzt ist.

- 45 **56.** Mobile Zellen-Sender/Empfänger-Einheit nach Anspruch 53, bei der der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors α unter Verwendung der folgenden Beziehung umfaßt:

$$\alpha = 0,125(1 + r_v),$$

45 wobei

$$r_v = (E_v - E_c)/(E_v + E_c)$$

50 wobei E_v die Energie des Tonhöhen-Codevektors ist und E_c die Energie des innovativen Codevektors ist.

- 55 **57.** Mobile Zellen-Sender/Empfänger-Einheit nach Anspruch 51, bei der das Innovationsfilter eine Übertragungsfunktion der folgenden Form besitzt:

$$F(z) = 1 - \sigma z^{-1}$$

wobei σ ein Periodizitätsfaktor ist, der von einem Periodizitätsniveau des Erregungssignals abgeleitet ist.

EP 1 125 285 B1

- 58.** Mobile Zellen-Sender/Empfänger-Einheit nach Anspruch 57, bei der der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors σ unter Verwendung der folgenden Beziehung umfaßt:

$$5 \quad \sigma = 2qR_p,$$

beschränkt durch $\sigma < 2q$,
wobei q ein Verbesserungsfaktor ist und wobei

$$10 \quad R_p = \frac{b^2 \mathbf{v}_T^t \mathbf{v}_T}{\mathbf{u}^t \mathbf{u}} = \frac{b^2 \sum_{n=0}^{N-1} \mathbf{v}_T^2(n)}{\sum_{n=0}^{N-1} \mathbf{u}^2(n)}$$

$$15$$

wobei \mathbf{v}_T der Tonhöhen-Codevektor ist, b eine Tonhöhenverstärkung ist, N eine Unterrahmenlänge ist und \mathbf{u} das Erregungssignal ist.

- 59.** Mobile Zellen-Sender/Empfänger-Einheit nach Anspruch 58, bei der der Verbesserungsfaktor q auf 0,25 gesetzt ist.
- 60.** Mobile Zellen-Sender/Empfänger-Einheit nach Anspruch 57, bei der der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors σ unter Verwendung der folgenden Beziehung umfaßt:

$$20 \quad \sigma = 0,25(1 + r_v),$$

30 wobei

$$r_v = (E_v - E_c)/(E_v + E_c)$$

35 wobei E_v die Energie des Tonhöhen-Codevektors ist und E_c die Energie des innovativen Codevektors ist.

- 61.** Zellennetzelement, das umfaßt:
- 40** a) einen Sender, der einen Codierer zum Codieren eines Breitbandsignals und eine Sendeschaltung zum Senden des codierten Breitbandsignals enthält; und
 - b) einen Empfänger, der eine Empfängerschaltung zum Empfangen eines gesendeten codierten Breitbandsignals und einen Decodierer nach Anspruch 21 zum Decodieren des empfangenen decodierten Breitbandsignals enthält.
- 45** **62.** Zellennetzelement nach Anspruch 61, bei dem der Faktorgenerator eine Einrichtung zum Berechnen eines Periodizitätsfaktors in Reaktion auf den Tonhöhen-Codevektor und den innovativen Codevektor umfaßt.
- 63.** Zellennetzelement nach Anspruch 61, bei dem das Innovationsfilter eine Übertragungsfunktion der folgenden Form besitzt:

$$50 \quad F(z) = -\alpha z + 1 - \alpha z^{-1}$$

wobei α ein Periodizitätsfaktor ist, der von dem Periodizitätsniveau des Erregungssignals abgeleitet ist.

- 55** **64.** Zellennetzelement nach Anspruch 63, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors α unter Verwendung der folgenden Beziehung umfaßt:

EP 1 125 285 B1

$$\alpha = qR_p,$$

- 5 beschränkt durch $\alpha < q$,
wobei q ein Verbesserungsfaktor ist und wobei

$$10 R_p = \frac{b^2 \mathbf{v}_T^t \mathbf{v}_T}{\mathbf{u}^t \mathbf{u}} = \frac{b^2 \sum_{n=0}^{N-1} \mathbf{v}_T^2(n)}{\sum_{n=0}^{N-1} \mathbf{u}^2(n)}$$

- 15 wobei \mathbf{v}_T der Tonhöhen-Codevektor ist, b eine Tonhöhenverstärkung ist, N eine Unterrahmenlänge ist und \mathbf{u} das Erregungssignal ist.

- 20 65. Zellennetzelement nach Anspruch 64, bei dem der Verbesserungsfaktor auf 0,25 gesetzt ist.
 66. Zellennetzelement nach Anspruch 63, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors α unter Verwendung der folgenden Beziehung umfaßt:

$$25 \quad \alpha = 0,125(1 + r_v),$$

wobei

$$30 \quad r_v = (E_v - E_c)/(E_v + E_c)$$

wobei E_v die Energie des Tonhöhen-Codevektors ist und E_c die Energie des innovativen Codevektors ist.

- 35 67. Zellennetzelement nach Anspruch 61, bei dem das innovationsfilter eine Übertragungsfunktion der folgenden Form besitzt:

$$F(z) = 1 - \sigma z^{-1}$$

- 40 wobei σ ein Periodizitätsfaktor ist, der von einem Periodizitätsniveau des Erregungssignals abgeleitet ist.

68. Zellennetzelement nach Anspruch 67, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors α unter Verwendung der folgenden Beziehung umfaßt:

$$45 \quad \sigma = 2qR_p,$$

beschränkt durch $\sigma < 2q$,
wobei q ein Verbesserungsfaktor ist und wobei

$$50 \quad 55 R_p = \frac{b^2 \mathbf{v}_T^t \mathbf{v}_T}{\mathbf{u}^t \mathbf{u}} = \frac{b^2 \sum_{n=0}^{N-1} \mathbf{v}_T^2(n)}{\sum_{n=0}^{N-1} \mathbf{u}^2(n)}$$

EP 1 125 285 B1

wobei \mathbf{v}_T der Tonhöhen-Codevektor ist, b eine Tonhöhenverstärkung ist, N eine Unterrahmenlänge ist und \mathbf{u} das Erregungssignal ist.

- 5 69. Zellennetzelement nach Anspruch 68, bei dem der Verbesserungsfaktor q auf 0,25 gesetzt ist.
 70. Zellennetzelement nach Anspruch 67, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors σ unter Verwendung der folgenden Beziehung umfaßt:

$$10 \quad \sigma = 0,25(1 + r_v),$$

wobei

$$15 \quad r_v = (E_v - E_c)/(E_v + E_c)$$

wobei E_v die Energie des Tonhöhen-Codevektors ist und E_c die Energie des innovativen Codevektors ist.

- 20 71. Bidirektionales drahtloses Kommunikationsundersystem mit einem Zellenkommunikationssystem für die Bedienung eines großen geographischen Gebiets, das in mehrere Zellen unterteilt ist, wobei das Untersystem umfaßt: mobile Sender/Empfänger-Einheiten; Zellenbasisstationen, die sich in den jeweiligen Zellen befinden; und ein Steuerendgerät zum Steuern der Kommunikation zwischen den Zellenbasisstationen;
 25 wobei sich das bidirektionale drahtlose Kommunikationsundersystem zwischen jeder Mobileinheit, die sich in einer Zelle befindet, und der Zellenbasisstation der einen Zelle befindet, wobei das bidirektionale drahtlose Kommunikationsundersystem sowohl in der Mobileinheit als auch in der Zellenbasisstation umfaßt:
 30 a) einen Sender, der einen Codierer zum Codieren eines Breitbandsignals und eine Sendeschaltung zum Senden des codierten Breitbandsignals enthält; und
 b) einen Empfänger, der eine Empfängerschaltung zum Empfangen eines gesendeten codierten Breitbandsignals und einen Decodierer nach Anspruch 21 zum Decodieren des empfangen codierten Breitbandsignals enthält.

- 35 72. Bidirektionales drahtloses Kommunikationsundersystem nach Anspruch 71, bei dem der Faktorgenerator eine Einrichtung zum Berechnen eines Periodizitätsfaktors in Reaktion auf den Tonhöhen-Codevektor und den innovativen Codevektor umfaßt.

- 40 73. Bidirektionales drahtloses Kommunikationsundersystem nach Anspruch 71, bei dem das Innovationsfilter eine Übertragungsfunktion der folgenden Form besitzt:

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

wobei α ein Periodizitätsfaktor ist, der von dem Periodizitätsniveau des Erregungssignals abgeleitet ist.

- 45 74. Bidirektionales drahtloses Kommunikationsundersystem nach Anspruch 73, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors α unter Verwendung der folgenden Beziehung umfaßt:

$$50 \quad \alpha = qR_p,$$

55 beschränkt durch $\alpha < q$,
 wobei q ein Verbesserungsfaktor ist und wobei

$$R_p = \frac{b^2 \mathbf{v}_T^t \mathbf{v}_T}{\mathbf{u}^t \mathbf{u}} = \frac{b^2 \sum_{n=0}^{N-1} \mathbf{v}_T^2(n)}{\sum_{n=0}^{N-1} \mathbf{u}^2(n)}$$

10 wobei \mathbf{v}_T der Tonhöhen-Codevektor ist, b eine Tonhöhenverstärkung ist, N eine Unterrahmenlänge ist und \mathbf{u} das Erregungssignal ist.

15 75. Bidirektionales drahtloses Kommunikationsundersystem nach Anspruch 74, bei dem der Verstärkungsfaktor q auf 0,25 gesetzt ist.

16 76. Bidirektionales drahtloses Kommunikationsundersystem nach Anspruch 73, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors α unter Verwendung der folgenden Beziehung umfaßt:

20
$$\alpha = 0,125(1 + r_v),$$

wobei

25
$$r_v = (E_v - E_c)/(E_v + E_c)$$

wobei E_v die Energie des Tonhöhen-Codevektors ist und E_c die Energie des innovativen Codevektors ist.

30 77. Bidirektionales drahtloses Kommunikationsundersystem nach Anspruch 71, bei dem das Innovationsfilter eine Übertragungsfunktion der folgenden Form besitzt:

$$F(z) = 1 - \sigma z^{-1}$$

35 wobei σ ein Periodizitätsfaktor ist, der von dem Periodizitätsniveau des Erregungssignals abgeleitet ist.

78. Bidirektionales drahtloses Kommunikationsundersystem nach Anspruch 77, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors σ unter Verwendung der folgenden Beziehung umfaßt:

40
$$\sigma = 2qR_p,$$

beschränkt durch $\sigma < 2q$,

wobei q ein Verbesserungsfaktor ist und wobei

45

$$R_p = \frac{b^2 \mathbf{v}_T^t \mathbf{v}_T}{\mathbf{u}^t \mathbf{u}} = \frac{b^2 \sum_{n=0}^{N-1} \mathbf{v}_T^2(n)}{\sum_{n=0}^{N-1} \mathbf{u}^2(n)}$$

55 wobei \mathbf{v}_T der Tonhöhen-Codevektor ist, b eine Tonhöhenverstärkung ist, N eine Unterrahmenlänge ist und \mathbf{u} das Erregungssignal ist.

79. Bidirektionales drahtloses Kommunikationsundersystem nach Anspruch 78, bei dem der Verbesserungsfaktor q

auf 0,25 gesetzt ist.

80. Bidirektionales drahtloses Kommunikationsundersystem nach Anspruch 77, bei dem der Faktorgenerator eine Einrichtung zum Berechnen des Periodizitätsfaktors σ unter Verwendung der folgenden Beziehung umfaßt:

5

$$\sigma = 0,25(1 + r_v),$$

wobei

10

$$r_v = (E_v - E_c)/(E_v + E_c)$$

wobei E_v die Energie des Tonhöhen-Codevektors ist und E_c die Energie des innovativen Codevektors ist.

15

Revendications

1. Un dispositif pour rehausser la périodicité d'un signal d'excitation produit en relation avec un vecteur de code de hauteur tonale et un vecteur de code d'innovation pour alimenter un filtre de synthèse de signal afin de synthétiser un signal large-bande, ledit dispositif de rehaussement de périodicité comprenant :

20

a) un générateur de facteur (204) pour calculer un facteur de périodicité relié au signal large-bande; et
b) un filtre d'innovation (205) pour filtrer le vecteur de code d'innovation en relation avec ledit facteur de périodicité pour ainsi réduire l'énergie d'une portion basse fréquence du vecteur de code d'innovation et rehausser la périodicité d'une portion basse fréquence du signal d'excitation.

25

2. Un dispositif de rehaussement de périodicité tel que défini dans la revendication 1, dans lequel ledit générateur de facteur comporte un moyen pour calculer un facteur de périodicité en réponse au vecteur de code de hauteur tonale et au vecteur de code d'innovation.

30

3. Un dispositif de rehaussement de périodicité tel que défini dans la revendication 1, dans lequel ledit filtre d'innovation a une fonction de transfert de la forme :

35

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

où α est un facteur de périodicité dérivé d'un niveau de périodicité du signal d'excitation.

40

4. Un dispositif de rehaussement de périodicité tel que défini dans la revendication 3, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité α utilisant la relation :

$$\alpha = q R_p$$

45

borné par $\alpha < q$, où q est un facteur de rehaussement, et où

50

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

55

où v_T est le vecteur de code de hauteur tonale, b est un gain de hauteur tonale, N est une longueur de sous-trame, et u est le signal d'excitation.

5. Un dispositif de rehaussement de périodicité tel que défini dans la revendication 4, dans lequel ledit facteur de

EP 1 125 285 B1

rehaussement q est fixé à 0.25.

6. Un dispositif de rehaussement de périodicité tel que défini dans la revendication 3, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité α utilisant la relation :

5

$$\alpha = 0.125 (1+r_v),$$

où

10

$$r_v = (E_v - E_c)/(E_v + E_c)$$

où E_v est l'énergie du vecteur de code de hauteur tonale et E_c est l'énergie du vecteur de code d'innovation.

15

7. Un dispositif de rehaussement de périodicité tel que défini dans la revendication 1, dans lequel ledit filtre d'innovation a une fonction de transfert de la forme :

20

$$F(z) = 1 - \sigma z^{-1}$$

où σ est un facteur de périodicité dérivé d'un niveau de périodicité du signal d'excitation.

25

8. Un dispositif de rehaussement de périodicité tel que défini dans la revendication 7, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité σ utilisant la relation :

$$\sigma = 2qR_p$$

30

borné par $\sigma < 2q$, où q est un facteur de rehaussement, et où

35

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

40

où v_T est le vecteur de code de hauteur tonale, b est un gain de hauteur tonale, N est une longueur de sous-trame, et u est le signal d'excitation.

45

9. Un dispositif de rehaussement de périodicité tel que défini dans la revendication 8, dans lequel ledit facteur de rehaussement q est fixé à 0.25.
10. Un dispositif de rehaussement de périodicité tel que défini dans la revendication 7, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité σ utilisant la relation :

50

$$\sigma = 0.25(1+r_v),$$

où

$$r_v = (E_v - E_c)/(E_v + E_c)$$

55

où E_v est l'énergie du vecteur de code de hauteur tonale et E_c est l'énergie du vecteur de code d'innovation.

11. Une méthode pour rehausser la périodicité d'un signal d'excitation produit en relation avec un vecteur de code de

EP 1 125 285 B1

hauteur tonale et un vecteur de code d'innovation pour alimenter un filtre de synthèse de signal afin de synthétiser un signal large-bande, ladite méthode de rehaussement de périodicité comprenant les étapes suivantes:

- 5 a) calculer un facteur de périodicité relié au signal large-bande; et
- b) filtrer le vecteur de code d'innovation en relation avec ledit facteur de périodicité pour ainsi réduire l'énergie d'une portion basse fréquence du vecteur de code d'innovation et rehausser la périodicité d'une portion basse fréquence du signal d'excitation.

10 **12.** Une méthode pour rehausser la périodicité telle que définie dans la revendication 11, dans laquelle ladite étape de calcul comporte le calcul d'un facteur de périodicité en réponse au vecteur de code de hauteur tonale et au vecteur de code d'innovation.

15 **13.** Une méthode pour rehausser la périodicité telle que définie dans la revendication 11, dans laquelle ledit filtrage comporte un traitement du vecteur d'innovation à travers un filtre d'innovation ayant une fonction de transfert de la forme :

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

20 où α est un facteur de périodicité dérivé d'un niveau de périodicité du signal d'excitation.

25 **14.** Une méthode pour rehausser la périodicité telle que définie dans la revendication 13, dans laquelle ledit calcul de facteur de périodicité comporte un calcul dudit facteur de périodicité α utilisant la relation :

$$\alpha = qR_p$$

30 borné par $\alpha < q$, où q est un facteur de rehaussement, et où

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

35 où v_T est le vecteur de code de hauteur tonale, b est un gain de hauteur tonale, N est une longueur de sous-trame, et u est le signal d'excitation.

40 **15.** Une méthode pour rehausser la périodicité telle que définie dans la revendication 14, dans laquelle ledit facteur de rehaussement q est fixé à 0.25.

45 **16.** Une méthode pour rehausser la périodicité telle que définie dans la revendication 13, dans laquelle ledit calcul du facteur de périodicité comprend un calcul dudit facteur de périodicité α utilisant la relation :

$$\alpha = 0.125(1+r_v),$$

50 où

$$r_v = (E_v - E_c)/(E_v + E_c)$$

55 où E_v est l'énergie du vecteur de code de hauteur tonale et E_c est l'énergie du vecteur de code d'innovation.

17. Une méthode pour rehausser la périodicité telle que définie dans la revendication 11, dans laquelle ledit filtrage comprend un traitement du vecteur d'innovation à travers un filtre d'innovation ayant une fonction de transfert de la forme :

$$F(z)=1-\sigma z^{-1}$$

où σ est un facteur de périodicité dérivé d'un niveau de périodicité du signal d'excitation.

5

- 18.** Une méthode pour rehausser la périodicité telle que définie dans la revendication 17, dans laquelle ledit calcul du facteur de périodicité comporte un calcul dudit facteur de périodicité σ utilisant la relation :

10

$$\sigma = 2qR_p$$

borné par $\sigma < 2q$, où q est un facteur de rehaussement, et où

15

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

20

où v_T est le vecteur de code de hauteur tonale, b est un gain de hauteur tonale, N est une longueur de sous-trame, et u est le signal d'excitation.

25

- 19.** Une méthode pour rehausser la périodicité telle que définie dans la revendication 18, dans laquelle ledit facteur de rehaussement q est fixé à 0.25.
- 20.** Une méthode pour rehausser la périodicité telle que définie dans la revendication 17, dans laquelle ledit calcul du facteur de périodicité comprend un calcul dudit facteur de périodicité σ utilisant la relation :

30

$$\sigma = 0.25 (1+r_v),$$

où

35

$$r_v = (E_v - E_c) / (E_v + E_c)$$

où E_v est l'énergie du vecteur de code de hauteur tonale et E_c est l'énergie du vecteur de code d'innovation.

40

- 21.** Un décodeur pour produire un signal large-bande synthétisé, comprenant :

45

- a) un dispositif de fragmentation de signal pour recevoir un signal large-bande codé et extraire dudit signal large-bande codé au moins des paramètres de répertoire de hauteur tonale, des paramètres de répertoire d'innovation, et des coefficients de filtre de synthèse;
- b) un répertoire de hauteur tonale pour, en réponse auxdits paramètres de répertoire de hauteur tonale, produire un vecteur de code de hauteur tonale;
- c) un répertoire d'innovation pour, en réponse auxdits paramètres de répertoire d'innovation, produire un vecteur de code d'innovation;
- d) un dispositif de rehaussement de périodicité tel que défini dans la revendication 1, comprenant ledit générateur de facteur pour calculer un facteur de périodicité relié au signal large-bande, et ledit filtre d'innovation pour filtrer le vecteur de code d'innovation;
- e) un circuit de combinaison pour combiner ledit vecteur de code de hauteur tonale et ledit vecteur de code d'innovation filtré par ledit filtre d'innovation pour ainsi produire ledit signal d'excitation ayant une périodicité rehaussée; et
- f) un filtre de synthèse de signal pour filtrer ledit signal d'excitation ayant une périodicité rehaussée en relation avec lesdits coefficients de filtre de synthèse pour ainsi produire ledit signal large-bande synthétisé.

22. Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 21, dans lequel ledit générateur de facteur comporte un moyen pour calculer un facteur de périodicité en réponse au vecteur de code de hauteur tonale et au vecteur de code d'innovation.
- 5 23. Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 21, dans lequel ledit filtre d'innovation a une fonction de transfert de la forme :

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

10

où α est un facteur de périodicité dérivé d'un niveau de périodicité du signal d'excitation.

15

24. Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 23, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité α utilisant la relation :

15

$$\alpha = qR_p$$

20

borné par $\alpha < q$, où q est un facteur de rehaussement, et où

25

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

30

où v_T est le vecteur de code de hauteur tonale, b est un gain de hauteur tonale, N est une longueur de sous-trame, et u est le signal d'excitation.

30

25. Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 24, dans lequel ledit facteur de rehaussement q est fixé à 0.25.
26. Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 23, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité α utilisant la relation :

35

$$\alpha = 0.125 (1+r_v),$$

40

où

$$r_v = (E_v - E_c)/(E_v + E_c)$$

45

où E_v est l'énergie du vecteur de code de hauteur tonale et E_c est l'énergie du vecteur de code d'innovation.

50

27. Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 21, dans lequel ledit filtre d'innovation a une fonction de transfert de la forme :

$$F(z) = 1 - \sigma z^{-1}$$

55

où σ est un facteur de périodicité dérivé d'un niveau de périodicité du signal d'excitation.

55

28. Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 27, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité σ utilisant la relation :

$$\sigma = 2qR_p$$

borné par $\sigma < 2q$, où q est un facteur de rehaussement, et où

5

10

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

où v_T est le vecteur de code de hauteur tonale, b est un gain de hauteur tonale, N est une longueur de sous-trame, et u est le signal d'excitation.

15 29. Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 28, dans lequel ledit facteur de rehaussement q est fixé à 0.25.

20 30. Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 27, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité σ utilisant la relation :

$$\sigma = 0.25 (1+r_v),$$

25

où

$$r_v = (E_v - E_c)/(E_v + E_c)$$

30

où E_v est l'énergie du vecteur de code de hauteur tonale et E_c est l'énergie du vecteur de code d'innovation.

35 31. Un décodeur pour produire un signal large-bande synthétisé, comprenant :

- 35 a) un dispositif de fragmentation de signal pour recevoir un signal large-bande codé et extraire dudit signal large-bande codé au moins des paramètres de répertoire de hauteur tonale, des paramètres de répertoire d'innovation, et des coefficients de filtre de synthèse;
- 35 b) un répertoire de hauteur tonale pour, en réponse auxdits paramètres de répertoire de hauteur tonale, produire un vecteur de code de hauteur tonale;
- 40 c) un répertoire d'innovation pour, en réponse auxdits paramètres de répertoire d'innovation, produire un vecteur de code d'innovation;
- 40 d) un circuit de combinaison pour combiner ledit vecteur de code de hauteur tonale et ledit vecteur de code d'innovation pour ainsi produire un signal d'excitation; et
- 45 e) un filtre de synthèse de signal pour filtrer ledit signal d'excitation en relation avec lesdits coefficients de filtre de synthèse pour ainsi produire ledit signal large-bande synthétisé;

le décodeur comprenant en outre un dispositif de rehaussement de périodicité tel que défini dans la revendication 1, comprenant un générateur de facteur pour calculer un facteur de périodicité relié au signal large-bande, et ledit filtre d'innovation pour filtrer le vecteur de code d'innovation.

50

32. Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 31, dans lequel ledit générateur de facteur comporte un moyen pour calculer un facteur de périodicité en réponse au vecteur de code de hauteur tonale et au vecteur de code d'innovation.

55 33. Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 31, dans lequel ledit filtre d'innovation a une fonction de transfert de la forme :

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

où α est un facteur de périodicité dérivé d'un niveau de périodicité du signal d'excitation.

5

- 34.** Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 33, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité α utilisant la relation :

10

$$\alpha = qR_p$$

borné par $\alpha < q$, où q est un facteur de rehaussement, et où

15

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

20

où v_T est le vecteur de code de hauteur tonale, b est un gain de hauteur tonale, N est une longueur de sous-trame, et u est le signal d'excitation.

25

- 35.** Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 34, dans lequel ledit facteur de rehaussement q est fixé à 0.25.

- 36.** Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 33, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité α utilisant la relation :

30

$$\alpha = 0.125 (1+r_v),$$

où

35

$$r_v = (E_v - E_c) / (E_v + E_c)$$

où E_v est l'énergie du vecteur de code de hauteur tonale et E_c est l'énergie du vecteur de code d'innovation.

40

- 37.** Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 31, dans lequel ledit filtre d'innovation a une fonction de transfert de la forme :

$$F(z) = 1 - \sigma z^{-1}$$

45

où σ est un facteur de périodicité dérivé d'un niveau de périodicité du signal d'excitation.

- 38.** Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 37, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité σ utilisant la relation :

50

$$\sigma = 2qR_p$$

borné par $\sigma < 2q$, où q est un facteur de rehaussement, et où

55

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

5

où v_T est le vecteur de code de hauteur tonale, b est un gain de hauteur tonale, N est une longueur de sous-trame, et u est le signal d'excitation.

10

39. Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 38, dans lequel ledit facteur de rehaussement q est fixé à 0.25.

15

40. Un décodeur pour produire un signal large-bande synthétisé tel que défini dans la revendication 37, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité σ utilisant la relation :

$$\sigma = 0.25 (1+r_v),$$

20

où

$$r_v = (E_v - E_c) / (E_v + E_c)$$

25

où E_v est l'énergie du vecteur de code de hauteur tonale et E_c est l'énergie du vecteur de code d'innovation.

41. Un système de communication cellulaire pour desservir une grande surface géographique divisée en une pluralité de cellules, comportant :

30

- a) des unités de transmission/réception mobiles;
- b) des stations de base cellulaires respectivement situées dans lesdites cellules;
- c) un terminal de contrôle pour contrôler la communication entre les stations de base cellulaires;
- d) un sous-système de communication sans fil bidirectionnel entre chaque unité mobile située à l'intérieur d'une cellule et la station de base cellulaire de ladite cellule, ledit sous-système de communication sans fil bidirectionnel comprenant, dans l'unité mobile et aussi dans la station de base cellulaire :

35

- i) un transmetteur incluant un codeur pour coder un signal large-bande et un circuit de transmission pour transmettre le signal large-bande codé; et
- ii) un récepteur incluant un circuit de réception pour recevoir un signal large-bande codé transmis et un décodeur tel que défini dans la revendication 21 pour décoder le signal large-bande codé reçu.

40

42. Un système de communication cellulaire tel que défini dans la revendication 41, dans lequel ledit générateur de facteur comporte un moyen pour calculer un facteur de périodicité en réponse au vecteur de code de hauteur tonale et au vecteur de code d'innovation.

45

43. Un système de communication cellulaire tel que défini dans la revendication 41, dans lequel ledit filtre d'innovation a une fonction de transfert de la forme :

50

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

où α est un facteur de périodicité dérivé d'un niveau de périodicité du signal d'excitation.

55

44. Un système de communication cellulaire tel que défini dans la revendication 43, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité α utilisant la relation :

$$\alpha = q R_p$$

EP 1 125 285 B1

borné par $\alpha < q$, où q est un facteur de rehaussement, et où

$$5 \quad R_p = \frac{b^2 v_T^t v_T}{u^t u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

10 où v_T est le vecteur de code de hauteur tonale, b est un gain de hauteur tonale, N est une longueur de sous-trame, et u est le signal d'excitation.

15 **45.** Un système de communication cellulaire tel que défini dans la revendication 44, dans lequel ledit facteur de rehaussement q est fixé à 0.25.

46. Un système de communication cellulaire tel que défini dans la revendication 43, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité α utilisant la relation :

20
$$\alpha = 0.125 (1+r_v),$$

où

25
$$r_v = (E_v - E_c) / (E_v + E_c)$$

où E_v est l'énergie du vecteur de code de hauteur tonale et E_c est l'énergie du vecteur de code d'innovation.

30 **47.** Un système de communication cellulaire tel que défini dans la revendication 41, dans lequel ledit filtre d'innovation a une fonction de transfert de la forme :

$$F(z) = 1 - \sigma z^{-1}$$

35 où σ est un facteur de périodicité dérivé d'un niveau de périodicité du signal d'excitation.

48. Un système de communication cellulaire tel que défini dans la revendication 47, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité σ utilisant la relation :

40
$$\sigma = 2qR_p$$

borné par $\sigma < 2q$, où q est un facteur de rehaussement, et où

45
$$R_p = \frac{b^2 v_T^t v_T}{u^t u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

50 où v_T est le vecteur de code de hauteur tonale, b est un gain de hauteur tonale, N est une longueur de sous-trame, et u est le signal d'excitation.

55 **49.** Un système de communication cellulaire tel que défini dans la revendication 48, dans lequel ledit facteur de rehaussement q est fixé à 0.25.

50. Un système de communication cellulaire tel que défini dans la revendication 47, dans lequel ledit générateur de

EP 1 125 285 B1

facteur comprend un moyen pour calculer ledit facteur de périodicité σ utilisant la relation :

$$\sigma = 0.25 (1+r_v),$$

5

où

$$r_v = (E_v - E_c)/(E_v + E_c)$$

10

où E_v est l'énergie du vecteur de code de hauteur tonale et E_c est l'énergie du vecteur de code d'innovation.

51. Une unité de transmission/réception mobile cellulaire comprenant :

15

- a) un transmetteur incluant un codeur pour coder un signal large-bande et un circuit de transmission pour transmettre le signal large-bande codé; et
- b) un récepteur incluant un circuit de réception pour recevoir un signal large-bande codé transmis et un décodeur tel que défini dans la revendication 21 pour décoder le signal large-bandé codé reçu.

20

52. Une unité de transmission/réception mobile cellulaire telle que définie dans la revendication 51, dans laquelle ledit générateur de facteur comporte un moyen pour calculer un facteur de périodicité en réponse au vecteur de code de hauteur tonale et au vecteur de code d'innovation.

25

53. Une unité de transmission/réception mobile cellulaire telle que définie dans la revendication 51, dans laquelle ledit filtre d'innovation a une fonction de transfert de la forme :

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

30

où α est un facteur de périodicité dérivé d'un niveau de périodicité du signal d'excitation.

54. Une unité de transmission/réception mobile cellulaire telle que définie dans la revendication 53, dans laquelle ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité α utilisant la relation :

35

$$\alpha = q R_p$$

borné par $\alpha < q$, où q est un facteur de rehaussement, et où

40

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

45

où v_T est le vecteur de code de hauteur tonale, b est un gain de hauteur tonale, N est une longueur de sous-trame, et u est le signal d'excitation.

50

55. Une unité de transmission/réception mobile cellulaire telle que définie dans la revendication 54, dans laquelle ledit facteur de rehaussement q est fixé à 0.25.

56. Une unité de transmission/réception mobile cellulaire telle que définie dans la revendication 53, dans laquelle ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité α utilisant la relation:

55

$$\alpha = 0.125 (1+r_v),$$

où

$$r_v = (E_v - E_c) / (E_v + E_c)$$

5

où E_v est l'énergie du vecteur de code de hauteur tonale et E_c est l'énergie du vecteur de code d'innovation.

57. Une unité de transmission/réception mobile cellulaire telle que définie dans la revendication 51, dans laquelle ledit filtre d'innovation a une fonction de transfert de la forme :

10

$$F(z)=1-\sigma z^{-1}$$

où σ est un facteur de périodicité dérivé d'un niveau de périodicité du signal d'excitation.

15

58. Une unité de transmission/réception mobile cellulaire telle que définie dans la revendication 57, dans laquelle ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité σ utilisant la relation :

20

$$\sigma = 2qR_p$$

borné par $\sigma < 2q$, où q est un facteur de rehaussement, et où

25

$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_f^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

30

où v_T est le vecteur de code de hauteur tonale, b est un gain de hauteur tonale, N est une longueur de sous-trame, et u est le signal d'excitation.

35

59. Une unité de transmission/réception mobile cellulaire telle que définie dans la revendication 58, dans laquelle ledit facteur de rehaussement q est fixé à 0.25.

60. Une unité de transmission/réception mobile cellulaire telle que définie dans la revendication 57, dans laquelle ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité σ utilisant la relation :

40

$$\sigma = 0.25(1+r_v),$$

où

45

$$r_v = (E_v - E_c) / (E_v + E_c)$$

où E_v est l'énergie du vecteur de code de hauteur tonale et E_c est l'énergie du vecteur de code d'innovation.

50

61. Un élément de réseau cellulaire comprenant :

- a) un transmetteur incluant un codeur pour coder un signal large-bande et un circuit de transmission pour transmettre le signal large-bande codé; et
- b) un récepteur incluant un circuit de réception pour recevoir un signal large-bande codé transmis et un décodeur tel que défini dans la revendication 21 pour décoder le signal large-bande codé reçu.

55

62. Un élément de réseau cellulaire tel que défini dans la revendication 61, dans lequel ledit générateur de facteur comporte un moyen pour calculer un facteur de périodicité en réponse au vecteur de code de hauteur tonale et au vecteur de code d'innovation.

63. Un élément de réseau cellulaire tel que défini dans la revendication 61, dans lequel ledit filtre d'innovation a une fonction de transfert de la forme:

$$5 \quad F(z) = -\alpha z + 1 - \alpha z^{-1}$$

où α est un facteur de périodicité dérivé d'un niveau de périodicité du signal d'excitation.

64. Un élément de réseau cellulaire tel que défini dans la revendication 63, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité α utilisant la relation :

$$\alpha = qR_p$$

15 borné par $\alpha < q$, où q est un facteur de rehaussement, et où

$$20 \quad R_p = \frac{b^2 v_T^\top v_T}{u^\top u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

25 où v_T est le vecteur de code de hauteur tonale, b est un gain de hauteur tonale, N est une longueur de sous-trame, et u est le signal d'excitation.

65. Un élément de réseau cellulaire tel que défini dans la revendication 64, dans lequel ledit facteur de rehaussement q est fixé à 0.25.

- 30 66. Un élément de réseau cellulaire tel que défini dans la revendication 63, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité α utilisant le relation :

$$\alpha = 0.125 (1 + r_v),$$

35 où

$$r_v = (E_v - E_c) / (E_v + E_c)$$

40 où E_v est l'énergie du vecteur de code de hauteur tonale et E_c est l'énergie du vecteur de code d'innovation.

67. Un élément de réseau cellulaire tel que défini dans la revendication 61, dans lequel ledit filtre d'innovation a une fonction de transfert de la forme :

$$45 \quad F(z) = 1 - \sigma z^{-1}$$

où σ est un facteur de périodicité dérivé d'un niveau de périodicité du signal d'excitation.

- 50 68. Un élément de réseau cellulaire tel que défini dans la revendication 67, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité σ utilisant la relation :

$$55 \quad \sigma = 2qR_p$$

borné par $\sigma < 2q$, où q est un facteur de rehaussement, et où

5

$$R_p = \frac{b^2 v_T^2 v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

10 où v_T est le vecteur de code de hauteur tonale, b est un gain de hauteur tonale, N est une longueur de sous-trame, et u est le signal d'excitation.

- 15
69. Un élément de réseau cellulaire tel que défini dans la revendication 68, dans lequel ledit facteur de rehaussement q est fixé à 0.25.
70. Un élément de réseau cellulaire tel que défini dans la revendication 67, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité σ utilisant la relation :

20

$$\sigma = 0.25 (1+r_v),$$

où

25

$$r_v = (E_v - E_c)/(E_v + E_c)$$

où E_v est l'énergie du vecteur de code de hauteur tonale et E_c est l'énergie du vecteur de code d'innovation.

30

71. Un sous-système de communication sans fil bidirectionnel avec un système de communication cellulaire pour desservir une grande surface géographique divisée en une pluralité de cellules, comportant : des unités de transmission/réception mobiles; des stations de base cellulaires, respectivement situées dans lesdites cellules; et un terminal de contrôle pour contrôler la communication entre les stations de base cellulaires;

35

ledit sous-système de communication sans fil bidirectionnel entre chaque unité mobile située à l'intérieur d'une cellule et la station de base cellulaire de ladite cellule, ledit sous-système de communication sans fil bidirectionnel comprenant, dans l'unité mobile et aussi dans la station de base cellulaire :

- 40
- a) un transmetteur incluant un codeur pour coder un signal large-bande et un circuit de transmission pour transmettre le signal large-bande codé; et
 - b) un récepteur incluant un circuit de réception pour recevoir un signal large-bande codé transmis et un décodeur tel que défini dans la revendication 21 pour décoder le signal large-bande codé reçu.

45

72. Un sous-système de communication sans fil bidirectionnel tel que défini dans la revendication 71, dans lequel ledit générateur de facteur comporte un moyen pour calculer un facteur de périodicité en réponse au vecteur de code de hauteur tonale et au vecteur de code d'innovation.

46

73. Un sous-système de communication sans fil bidirectionnel tel que défini dans la revendication 71, dans lequel ledit filtre d'innovation a une fonction de transfert de la forme :

50

$$F(z) = -\alpha z + 1 - \alpha z^{-1}$$

où α est un facteur de périodicité dérivé d'un niveau de périodicité du signal d'excitation.

55

74. Un sous-système de communication sans fil bidirectionnel tel que défini dans la revendication 73, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité α utilisant la relation :

$$\alpha = q R_p$$

EP 1 125 285 B1

borné par $\alpha < q$, où q est un facteur de rehaussement, et où

$$5 \quad R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

10 où v_T est le vecteur de code de hauteur tonale, b est un gain de hauteur tonale, N est une longueur de sous-trame, et u est le signal d'excitation.

- 15 **75.** Un sous-système de communication sans fil bidirectionnel tel que défini dans la revendication 74, dans lequel ledit facteur de rehaussement q est fixé à 0.25.
- 76.** Un sous-système de communication sans fil bidirectionnel tel que défini dans la revendication 73, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité α utilisant la relation :

20
$$\alpha = 0.125(1 + r_v),$$

où

25
$$r_v = (E_v - E_c) / (E_v + E_c)$$

où E_v est l'énergie du vecteur de code de hauteur tonale et E_c est l'énergie du vecteur de code d'innovation.

- 30 **77.** Un sous-système de communication sans fil bidirectionnel tel que défini dans la revendication 71, dans lequel ledit filtre d'innovation a une fonction de transfert de la forme:

$$F(z) = 1 - \sigma z^{-1}$$

35 où σ est un facteur de périodicité dérivé d'un niveau de périodicité du signal d'excitation.

- 78.** Un sous-système de communication sans fil bidirectionnel tel que défini dans la revendication 77, dans lequel ledit générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité σ utilisant la relation :

40
$$\sigma = 2qR_p$$

borné par $\sigma < 2q$, où q est un facteur de rehaussement, et où

45
$$R_p = \frac{b^2 v_T^T v_T}{u^T u} = \frac{b^2 \sum_{n=0}^{N-1} v_T^2(n)}{\sum_{n=0}^{N-1} u^2(n)}$$

50 où v_T est le vecteur de code de hauteur tonale, b est un gain de hauteur tonale, N est une longueur de sous-trame, et u est le signal d'excitation.

- 55 **79.** Un sous-système de communication sans fil bidirectionnel tel que défini dans la revendication 78, dans lequel ledit facteur de rehaussement q est fixé à 0.25.
- 80.** Un sous-système de communication sans fil bidirectionnel tel que défini dans la revendication 77, dans lequel ledit

EP 1 125 285 B1

générateur de facteur comprend un moyen pour calculer ledit facteur de périodicité σ utilisant la relation :

$$\sigma = 0.25 (1+r_v), \text{ où}$$

5

$$r_v = (E_v - E_c) / (E_v + E_c)$$

où E_v est l'énergie du vecteur de code de hauteur tonale et E_c est l'énergie du vecteur de code d'innovation.

10

15

20

25

30

35

40

45

50

55







